TITLE OF THE INVENTION

PHOTOSENSOR SYSTEM AND DRIVE CONTROL METHOD THEREOF

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a continuation-in-part

application of Application 09/703,025, filed October 31,

2000.

This application is based upon and claims the

benefit of priority from the prior Japanese Patent

Applications No. 11-316650, filed November 8, 1999;

No. 11-319605, filed November 10, 1999; No. 2000-015981,

filed January 25, 2000, and No. 2001-198615, filed June

29, 2001, the entire contents of which are incorporated

herein by reference.

BACKGROUND OF THE INVENTION

The present invention relates to a photosensor

system having a photosensor array constituted by

two-dimensionally arraying a plurality of photosensors,

and a drive control method thereof.

Imaging apparatuses such as electronic still

cameras, video cameras, and the like have come to be

very widely used. These imaging apparatuses employ

a solid-state imaging device, such as a CCD (Charge

Coupled Device), which serves as a photoelectric

converting device for converting an image of a to-be-

photographed subject into an image signal. As well

known, the CCD has a structure in which photosensors

(light receiving elements) such as photodiodes, or

thin film transistors (TFT: Thin Film Transistor) are arranged in a matrix, and the amount of electron-hole pairs (the amount of charge) generated corresponding to the amount of light entering the light receiving

5   section of each sensor is detected by a horizontal scanning circuit and vertical scanning circuit to detect the luminance of radiation.

In a photosensor system using such a CCD, it is necessary to respectively provide scanned photosensors

10   with selective transistors for causing the scanned photosensor to assume a selected state. In place of the combination of the photosensor and the selective transistor, a photosensor (to be referred to as a double-gate photosensor hereinafter) is now being

15   developed, which is formed of a thin film transistor having a so-called double-gate structure and has both a photosensing function and a selecting function.

FIG. 39A is a sectional view showing the structure of a double-gate photosensor 10. FIG. 39B is a circuit

20   diagram showing the equivalent circuit of the double-gate photosensor 10.

The double-gate photosensor 10 comprises a semiconductor thin film 11 formed of amorphous silicon or the like, n^+-silicon layers 17 and 18, source and

25   drain electrodes 12 and 13 respectively formed on the n^+-silicon layers 17 and 18, a top gate electrode 21 formed above the semiconductor thin film 11 via a block

insulating film 14 and upper gate insulating film 15,
a protective insulating film 20 provided on the top
gate electrode 21, and a bottom gate electrode 22
provided below the semiconductor thin film 11 via

5 a lower gate insulating film 16. The double-gate
photosensor 10 is provided on a transparent insulating
substrate 19 formed of glass or the like.

    In other words, the double-gate photosensor 10
includes an upper MOS transistor comprised of the

10 semiconductor thin film 11, source electrode 12, drain
electrode 13, and top gate electrode 21, and a lower
MOS transistor comprised of the semiconductor thin film
11, source electrode 12, drain electrode 13, and bottom
gate electrode 22. As shown in the equivalent circuit

15 of FIG. 31B, the double-gate photosensor 10
is considered to include two MOS transistors having
a common channel region formed of the semiconductor
thin film 11, TG (Top Gate terminal), BG (Bottom Gate
terminal), S (Source terminal), and D (drain Terminal).

20   The protective insulating film 20, top gate
electrode 21, upper gate insulating film 15, block
insulating film 14, and lower gate insulating film
16 are all formed of a material having a high
transmittance of visible light for activating the

25 semiconductor thin film 11. Light entering the sensor
from the top gate electrode 21 side passes through the
top gate electrode 21, upper gate insulating film 15,

and block insulating film 14, and then enters the semiconductor thin film 11, thereby generating and accumulating charges (positive holes) in the channel region.

5   FIG. 40 is a schematic view showing a photosensor system constituted by two-dimensionally arraying double-gate photosensors 10. As shown in FIG. 40, the photosensor system comprises a sensor array 100 that is constituted of a large number of double-gate

10   photosensors 10 arranged in an n $\times$ m matrix, top and bottom gate lines 101 and 102 that respectively connect the top gate terminals TG and bottom gate terminals BG of the double-gate photosensors 10 in a row direction, top and bottom gate drivers 111 and 112 respectively

15   connected to the top and bottom gate lines 101 and 102, data lines 103 that respectively connect the drain terminals D of the double-gate photosensors 10 in a column direction, and an output circuit section 113 connected to the data lines 103.

20   In FIG. 40, ϕtg and ϕbg represent control signals for generating a reset pulse ϕTi and readout pulse ϕBi, respectively, which will be described later, and ϕpg represents a pre-charge pulse for controlling the timing at which a pre-charge voltage Vpg is applied.

25   In the above-described structure, as described later, the photosensing function is realized by applying a predetermined voltage from the top gate

driver 111 to the top gate terminals TG, while the readout function is realized by applying a predetermined voltage from the bottom gate driver 112 to the bottom gate terminals BG, then sending the output voltage of the photosensors 10 to the output circuit section 113 via the data lines 103, and outputting serial data Vout.

FIGS. 41A to 41D are timing charts showing a method of controlling the photosensor system, and showing a detecting period (i-th row processing cycle) in the i-th row of the sensor array 100. First, a high-level pulse voltage (reset pulse; e.g., $Vtg = +15V$) ϕTi shown in FIG. 41A is applied to the top gate line 101 of the i-th row, and during a reset period T_{reset}, reset operation for discharging the double-gate photosensors 10 of the i-th row is executed.

Subsequently, a bias voltage ϕTi of low level (e.g., $Vtg = -15V$) is applied to the top gate line 101 of the i-th row, thereby finishing the reset period T_{reset} and starting a charge accumulating period Ta in which the channel region is charged. During the charge accumulating period Ta, charges (positive holes) corresponding to the amount of light entering each sensor from the top gate electrode side are accumulated in the channel region.

Then, a pre-charge pulse ϕpg shown in FIG. 41C with a pre-charge voltage Vpg is applied to the data

lines 103 during the charge accumulating period Ta, and after a pre-charge period T_{prch} for making the drain electrodes 13 keep a charge, a bias voltage (readout pulse ϕBi) of high level (e.g., Vbg = +10V) shown in FIG. 41B is applied to the bottom gate line 102 of the i-th row. At this time, the double-gate photosensors 10 of the i-th row are turned on to start a readout period T_{read}.

During the readout period T_{read}, the charges accumulated in the channel region serve to moderate a low-level voltage (e.g., Vtg = -15V) which has an opposite polarity of charges accumulated in the channel region and is applied to each top gate terminal TG. Therefore, an n-type channel is formed by the voltage Vbg at each bottom gate terminal BG, the voltage VD at the data lines 103 gradually reduces in accordance with the drain current with lapse of time after the pre-charge voltage Vpg is applied. More specifically, the tendency of change in the voltage VD at the data lines 103 depends upon the amount of received light in the case where the charge accumulating period Ta is constant. As shown in FIG. 41D, the voltage VD tends to gradually reduce when the incident light is dark, i.e., a small amount of light is received, and hence only small charges are accumulated, whereas the voltage VD tends to suddenly reduce when the incident light is bright, i.e., a large amount of light is received, and

hence large charges are accumulated. From this, it is understood that the amount of radiation can be calculated by detecting the voltage VD at the data lines 103 a predetermined period after the start of the readout period T_{read}, or by detecting a period required until the voltage VD reaches a predetermined threshold voltage. An image reading sensitivity corresponds to the charge accumulating period Ta. Assuming that the amount of light is constant, the amount of charge accumulated increases and the image reading sensitivity enhanced in accordance with an increase in the charge accumulating period Ta. Likewise, the amount of charge accumulated decreases and the image reading sensitivity degraded in accordance with a decrease in the charge accumulating period Ta.

Image reading is performed by sequentially executing the above-described drive-control for each line of the sensor array 100, by executing the control for each line in a parallel manner at different timings at which the driving pulses do not overlap.

Although the case of using the double-gate photosensor as a photosensor has been described above, even a photosensor system using a photodiode or phototransistor as a photosensor has operation steps: reset operation → charge accumulating operation → pre-charge operation → reading operation, and uses a similar drive sequence. The conventional photosensor

system as above has the following problems.

(1) To read a subject image in various use environments in a photosensor system using the above-described photosensor, the image reading sensitivity (charge accumulating period) must be properly set. The proper image reading sensitivity changes depending on changes in ambient conditions such as the illuminance of external light in a use environment, and also changes when the characteristics of the photosensor change. In the prior art, therefore, a circuit for detecting the illuminance of external light must be additionally arranged. Alternatively, a subject image is read at different image reading sensitivities before the start of normal reading operation of that subject image, and an optimal image reading sensitivity must be determined on the basis of a read result. However, a reading sensitivity setting method of unconditionally and automatically setting a proper image reading sensitivity based on a read result for every image reading sensitivity that is obtained by operations executed at different image reading sensitivities, has not been developed yet.

(2) If a foreign substance attaches to the sensing surface of a photosensor or a defect is generated in a photosensor element in setting the reading sensitivity based on the result of the sensitivity-adjusting reading operation, and a read result obtained for each

image reading sensitivity obtained in the reading operation is directly used, an abnormal value is contained in the read result, leading to failure to set a proper image reading sensitivity and to inhibit accurate reading operation of a subject image. For example, when this photosensor system is applied to a fingerprint reading apparatus, the apparatus may malfunction in fingerprint recognition processing.

BRIEF SUMMARY OF THE INVENTION

It is an object of the present invention to provide a reading sensitivity setting method of unconditionally and automatically setting a proper image reading sensitivity in order to accurately read a subject image in various use environments in a photosensor system. The present invention is advantageous in that any malfunction in setting the image reading sensitivity is prevented even if a foreign substance attaches to the sensing surface of a photosensor, or a photosensor element becomes defective.

To achieve the above advantage, a photosensor system according to the present invention comprises: a photosensor array constituted by two-dimensionally arranging a plurality of photosensors; an image reader which read a subject image by use of the photosensor array; a sensitivity-adjusting reader which read the subject image while changing the image reading

sensitivity of the photosensor array stepwise; optimal image reading sensitivity extracting means for extracting an optimal image reading sensitivity suitable for the image reading operation on the basis of a predetermined measurement amount relating to an image pattern of the subject image read by the sensitivity-adjusting reader; and reading sensitivity-setting means for setting the optimal image reading sensitivity to a reading sensitivity of the image reader.

According to the first reading sensitivity setting method of the present invention, the sensitivity-adjusting reader executes sensitivity-adjusting reading operation at a plurality of stages for, e.g., respective rows. The optimal image reading sensitivity-extracting means extracts an image reading sensitivity that allows the dynamic range of the measurement amount of each row to become maximal, on the basis of the predetermined measurement amount regarding the image pattern of the subject image. Alternatively, the optimal image reading sensitivity-extracting means extract a row in which the dynamic range becomes maximal and a displacement of the dynamic range between image reading sensitivity becomes minimal. The row is extracted in accordance with the dynamic range that is determined for each image reading sensitivity after high-frequency components

corresponding to a change in the dynamic range of the measurement amount of each row have been removed. The reading sensitivity-setting means sets the image reading sensitivity corresponding to the extracted row as an optimal sensitivity. This can reduce the amount of data subjected to the extraction processing of the optimal image reading sensitivity, simplify sensitivity setting processing, and shorten the required time. Even when the ambient light or the characteristics of the photosensor change, an optimal image reading sensitivity can be set in accordance with the changes. In addition, a suitable image reading sensitivity can be extracted without being adversely affected by a foreign substance attached to the sensing surface of the photosensor array, an abnormal pixel due to a defective element included in the photosensor element, or the like.

According to the second reading sensitivity setting method of the present invention, the sensitivity-adjusting reader changes the image reading sensitivity stepwise with respect to the photosensors of a specific row section of the photosensor array, and sensitivity-adjusting reading operation is performed by reading a subject image portion corresponding to the specific row section. Owing to this, the time needed for the sensitivity-adjusting reading operation can be as short as possible. In addition, the amount of data

used for the extraction of an optimal image reading

sensitivity can be significantly reduced, thereby

shortening the processing time.

In this case, abnormal pixel determining element

5   is provided for determining whether or not any abnormal

pixel exists in a specific row section by checking if

the measurement amount pertaining to the specific row

section and corresponding to each column changes when

the image reading sensitivity is switched from one to

10   another. Sensitivity-adjusting read controlling means

is also provided for executing sensitivity-adjusting

reading operation for a specific row section other than

the specific row section where the abnormal pixel is

determined to exist. With this structure, even if an

15   abnormal pixel exists in the specific row section for

which the sensitivity-adjusting reading operation is

performed, another specific row section is selected to

avoid the adverse effects the abnormal pixel may have.

Additional objects and advantages of the invention

20   will be set forth in the description which follows, and

in part will be obvious from the description, or may

be learned by practice of the invention. The objects

and advantages of the invention may be realized and

obtained by means of the instrumentalities and combina-

25   tions particularly pointed out hereinafter.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

The accompanying drawings, which are incorporated

in and constitute a part of the specification, illust-
rate presently preferred embodiments of the invention,
and together with the general description given above,
and the detailed description of the preferred embodi-

5   ments given below, serve to explain the principles of
the invention.

FIG. 1 is a block diagram showing an arrangement
of a photosensor system according to the present
invention;

10   FIG. 2 is a block diagram showing an arrangement
of a controller applied to the first embodiment;

FIG. 3 is a flow chart showing operation of the
first embodiment;

FIG. 4 is a view showing an example of image data

15   when a fingerprint image is read by sensitivity-
adjusting reading operation in the first embodiment;

FIGS. 5A to 5E are graphs each showing changes in
lightness data in a specific row that are obtained by
sensitivity-adjusting reading operation in the first

20   embodiment;

FIGS. 6A and 6B are views showing the relationship
between a table representing the dynamic range of
lightness data of each row that is obtained by
sensitivity-adjusting reading operation in the first

25   embodiment, and a corresponding row number vs. image
reading sensitivity correspondence table;

FIG. 7 is a view showing another example of image

data when a fingerprint image is read by sensitivity-adjusting reading operation in a modification of the first embodiment;

FIGS. 8A to 8E are graphs each showing changes in lightness data in the column range of a specific region in a specific row that are obtained by sensitivity-adjusting reading operation in the modification of the first embodiment;

FIGS. 9A and 9B are tables showing the relationship between a table representing the dynamic range of lightness data of each row that is obtained by sensitivity-adjusting reading operation in the modification of the first embodiment, and a corresponding row number vs. image reading sensitivity correspondence table;

FIG. 10 is a flow chart showing operation of the second embodiment;

FIG. 11 is a view showing an example of image data when a fingerprint image is read by sensitivity-adjusting reading operation in the second embodiment;

FIGS. 12A and 12B are graphs, respectively, showing the value of lightness data in a predetermined column that is obtained by sensitivity-adjusting reading operation in the second embodiment, and the differentiated value of lightness data between rows;

FIGS. 13A and 13B are views showing the relation-ship between a table representing the differentiated

value of lightness data between rows in a predetermined

column that is obtained by sensitivity-adjusting

reading operation in the second embodiment, and a

corresponding row number vs. image reading sensitivity

5　　correspondence table;

FIG. 14 is a flow chart showing operation of the

third embodiment;

FIG. 15 is a view showing examples of image data

and a sensitivity determination range when a finger-

10　　print image is read by sensitivity-adjusting reading

operation in the third embodiment;

FIG. 16 is a graph showing changes in lightness

data of a specific row in the sensitivity determination

range of image data read by sensitivity-adjusting

15　　reading operation in the third embodiment;

FIGS. 17A and 17B are graphs showing the

relationship between changes in the dynamic ranges of

respective rows of image data read by sensitivity-

adjusting reading operation in the third embodiment,

20　　and changes in the linearly differentiated values of

the dynamic ranges of respective rows;

FIGS. 18A and 18B are views showing the relation-

ship between a table representing the dynamic range

of each row and the linearly differentiated value of

25　　the dynamic range that are obtained by sensitivity-

adjusting reading operation in the third embodiment,

and a corresponding row number vs. image reading

sensitivity correspondence table;

FIGS. 19A and 19B are views showing the relation-
ship between a table representing the dynamic range
of each row and a corresponding row number vs. image
reading sensitivity correspondence table when the first
embodiment is applied to image data read by
sensitivity-adjusting reading operation in the third
embodiment;

FIG. 20 is a view showing a case wherein
an abnormal value exists in read image data of
a fingerprint image in sensitivity-adjusting reading
operation in the third embodiment;

FIG. 21 is a graph showing changes in the dynamic
ranges of respective rows when an abnormal value
exists in read image data of a fingerprint image in
sensitivity-adjusting reading operation in the third
embodiment;

FIGS. 22A and 22B are graphs showing the
relationship between changes in the dynamic ranges
of respective rows, and changes in the linearly
differentiated values of the dynamic ranges of
respective rows when an abnormal value exists in read
image data of a fingerprint image in sensitivity-
adjusting reading operation in the third embodiment;

FIG. 23 is a flow chart showing operation of the
fourth embodiment;

FIG. 24 is a block diagram showing an arrangement

of a controller applied to the fifth embodiment;

FIG. 25 is a flow chart showing operation of the fifth embodiment;

FIG. 26 is a view showing a case wherein an abnormal value across a plurality of rows exists in read image data of a fingerprint image in sensitivity-adjusting reading operation of the fifth embodiment;

FIG. 27A is a graph showing changes in the dynamic ranges of respective rows when an abnormal value across a plurality of rows exists in read image data of a fingerprint image in sensitivity-adjusting reading operation of the fifth embodiment, and the dynamic range discretely varies for respective rows;

FIG. 27B is a graph showing the dynamic range distribution of lightness data of respective rows after abnormal value removing operation in the fifth embodiment;

FIG. 28 is a flowchart illustrating operation of the sixth embodiment;

FIG. 29 shows a specific row section of a photosensor array for which sensitivity-adjusting reading operation is performed according to the sixth embodiment, the specific row section being illustrated in relation to a subject image;

FIGS. 30A to 30E are graphs showing how lightness data on a specific row section changes in the sixth embodiment, in relation to the number of times the

reading operation is performed;

FIG. 31 is a graph showing how a dynamic range changes in the sixth embodiment, in relation to the number of times the reading operation is performed;

FIG. 32 is a flowchart illustrating operation of the seventh embodiment;

FIG. 33 shows a specific row section of a photosensor array for which sensitivity-adjusting reading operation is performed according to the seventh embodiment, the specific row section being illustrated in relation to a subject image;

FIGS. 34A to 34E are graphs showing how lightness data on a specific row section changes in the seventh embodiment, in relation to the number of times the reading operation is performed; FIGS. 35A to 35J are timing charts showing the first embodiment of an image reading sensitivity setting method applied to sensitivity-adjusting reading operation executed in each of the first to fifth embodiments;

FIGS. 36A to 36J are timing charts showing the second embodiment of an image reading sensitivity setting method applied to sensitivity-adjusting reading operation executed in each of the first to fifth embodiments;

FIGS. 37A to 37L are timing charts illustrating an image reading sensitivity-setting method that is applicable to the sensitivity-adjusting reading

operation executed according to the sixth and seventh embodiments;

FIGS. 38A to 38H are timing charts showing an embodiment when an effective voltage adjusting period is set after sensitivity-adjusting reading operation and image reading periods in a photosensor system drive control method according to the present invention;

FIG. 39A is a sectional view showing the structure of a conventional double-gate photosensor;

FIG. 39B is an equivalent circuit diagram showing the double-gate photosensor;

FIG. 40 is a schematic view showing a photosensor system constituted by two-dimensionally arraying double-gate photosensors; and

FIGS. 41A to 41D are timing charts showing a conventional drive method for the double-gate photosensor system.

DETAILED DESCRIPTION OF THE INVENTION

Methods of controlling a photosensor system according to the present invention will be described in detail with reference to the several views of the accompanying drawings. Although in embodiments described below, a double-gate photosensor is applied as a photosensor, the present invention is not limited to the double-gate photosensor, but is also applicable to a photosensor system using another type of photosensor.

FIG. 1 is a block diagram showing an arrangement of a photosensor system according to the present invention. The double-gate photosensor shown in FIG. 39A is used, and the arrangement of the
5   photosensor system shown in FIG. 40 will be referred to if necessary. The same reference numerals as in the photosensor system shown in FIG. 40 denote the same parts.

As shown in FIG. 1, the photosensor system
10   according to an embodiment comprises a photosensor array 100 including double-gate photosensors 10 shown in FIG. 39A that are arrayed two-dimensionally, a top gate driver 111 for applying a predetermined reset pulse to a top gate terminal TG of each double-gate
15   photosensor 10 at a predetermined timing, a bottom gate driver 112 for applying a predetermined readout pulse to a bottom gate terminal BG of each double-gate photosensor 10 at a predetermined timing, an output circuit section 113 constituted by an amplifier 116,
20   and a column switch 114 and pre-charge switch 115 for reading a data line voltage and applying a pre-charge voltage to each double-gate photosensor 10, respectively, an analog/digital converter (to be referred to as an A/D converter hereinafter) 117 for converting the
25   read data voltage as an analog signal into image data as a digital signal, a controller 120 which is adopted to control the operation of reading a subject image by

the photosensor array 100, and to exchange data with
an external function section 200, and which controls
sensitivity setting in the present invention, and a RAM
130 that stores, for example, read image data, data
5   relating to setting of a reading sensitivity described
later.

The structure including the photosensor array 100,
top gate driver 111, bottom gate driver 112, and output
circuit section 113 is the same as and has the same
10 function as the photosensor system shown in FIG. 40.
In addition to this structure, this embodiment adopts
the A/D converter 117, controller 120, and RAM 130 to
enable various types of control as described below.

The controller 120 outputs control signals ϕtg
15 and ϕbg to the top and bottom gate drivers 111 and
112, respectively, which, in turn, output predetermined
voltages (reset pulse and readout pulse) to the top
gate terminal TG and bottom gate terminal BG of each
double-gate photosensor 10 of the photosensor array
20 100, respectively. The controller 120 also outputs
a control signal ϕpg to the pre-charge switch 115 to
control execution of the operation of reading a subject
image. A data line voltage read from the photosensor
array 100 via the column switch 114 and amplifier 116
25 is converted into a digital signal by the A/D converter
117, and supplied as image data. The controller 120
also has a function of executing predetermined image

processing for image data, writing or reading image data into or from the RAM 130. The controller 120 serves as an interface with the external function section 200 that executes predetermined processing such as image data identification, modification, and the like.

The controller 120 has another function of controlling control signals to be output to the top and bottom gate drivers 111 and 112 to set an optimal reading sensitivity for reading a subject image in accordance with ambient environments such as the illuminance of external light, i.e., an optimal charge accumulating period for each double-gate photosensor 10.

As will be described below, photosensor system drive control methods according to embodiments of the present invention are based on the arrangement of this photosensor system.

<First Embodiment>

The first embodiment of the photosensor system drive control method according to the present invention will be described with reference to the several views of the accompanying drawing.

FIG. 2 is a block diagram showing an arrangement of a controller 120 applied to the first embodiment. As shown in FIG. 2, the controller 120 comprises a device controller 121 for controlling a top gate driver

111, bottom gate driver 112, and output circuit section 113, a data controller 122 for managing various data such as image data, write data, and readout data to the RAM 130, and a main controller 123 which supervises the controllers 121 and 122 and interfaces with an external function section.

The controller 120 further comprises a data comparator 124 for comparing the sizes of specific measurement data based on image data input as a digital signal from a photosensor array 100 via an A/D converter 117 to extract maximum and minimum values, an adder 125 having a function of calculating, e.g., the difference between measurement data, a data selector 126 for receiving processed image data via the A/D converter 117, data comparator 124, and adder 125, and switching write/readout in/from the RAM, re-input to the data comparator 124 and adder 125, and output to the external function section via the data controller 122 in accordance with the received data, and a sensitivity setting register 127 for changing control signals to be output from the device controller 121 to the top and bottom gate drivers 111 and 112 so as to optimize the reading sensitivity of the photosensor array on the basis of a control signal from the data controller 122.

The operation of the first embodiment in the operation control method of the photosensor system

using the above controller 120 will be explained with
reference to FIG. 3. FIG. 3 is a flow chart showing an
operation up to read of a subject image with an optimal
sensitivity according to the first embodiment in
5   operation control of the photosensor system. This
operation will be described by properly referring to
the arrangement of the photosensor system shown in
FIGS. 1 and 2.

In S11 (sensitivity-adjusting reading operation)
10   of FIG. 3, the main controller 123 controls to set an
image reading sensitivity for sensitivity-adjusting
reading operation in the sensitivity setting register
127 via the data controller 122, and executes
sensitivity-adjusting reading operation for a subject
15   image. These operations are executed prior to normal
reading operation of a subject image, for example.
Similar to normal image reading operation, the
sensitivity-adjusting reading operation is done by
executing a series of processes: reset operation →
20   charge accumulating operation → pre-charge operation →
readout operation. In the pre-reading operation, the
image reading sensitivity is changed stepwise for,
e.g., respective rows of a subject image so as to read
one subject image at a plurality of different
25   sensitivities. The image reading sensitivities of
respective rows are stored in the RAM 130 in, e.g., a
table format (row number vs. image reading sensitivity

correspondence table) in correspondence with row
numbers. A detailed image reading sensitivity setting
method will be described later.

In S12 (image data conversion step) of FIG. 3, the
image data read by the sensitivity-adjusting reading
operation is converted into a digital signal via the
amplifier 116 and A/D converter 117, and input as
lightness data corresponding to the bright/dark pattern
of the subject image to the data comparator 124. In
this case, the lightness data is expressed by, e.g.,
256 gray levels.

In S13 (step of extracting the maximum and minimum
values of each row) of FIG. 3, the data comparator 124
extracts the maximum and minimum values of each row
from the lightness data input to the data comparator
124, and outputs them to the adder 125. That is, the
data comparator 124 extracts lightness data represent-
ing a maximum value (gray level value of the brightest
pixel) contained in each row, and lightness data
representing a minimum value (gray level value of the
darkest pixel).

In S14 (step of calculating the dynamic range
of each row) of FIG. 3, the adder 125 calculates as
a dynamic range the difference between the maximum and
minimum values of lightness data of each row, and
stores the dynamic range in the RAM 130 via the data
selector 126. The adder 125 executes dynamic range

calculation processing for all the rows.

In S15 (step of extracting a row number having a maximum dynamic range) of FIG. 3, the dynamic ranges of respective rows stored in the RAM 130 are read out

5   via the data selector 126, and input to the data comparator 124, which extracts a row number having the maximum dynamic range among the dynamic ranges of the respective rows.

In S16 (sensitivity referring/extraction step) of

10   FIG. 3, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is looked up based on the row number having the maximum dynamic range, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

15   In S17 (extracted sensitivity setting step) of FIG. 3, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity.

20   In S18 (subject image reading step) of FIG. 3, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the first embodiment of

25   the photosensor system drive control method using the above-described controller 120 to a fingerprint reading apparatus will be described with reference to FIGS. 4

to 6B.

FIG. 4 is a view showing an example of fingerprint image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIGS. 5A to 5E are graphs each showing changes in lightness data in several rows that are based on the subject image data obtained by the sensitivity-adjusting reading operation. FIGS. 6A and 6B are views for illustrating tables showing the relationship between the dynamic range of lightness data of each row that is obtained by pre-reading operation, and a row number vs. image reading sensitivity correspondence table. Assume that image data is read out in units of a matrix pattern of 256 rows × 196 columns. A larger lightness data value represents a brighter image, and a smaller lightness data value represents a darker image. In the sensitivity-adjusting reading operation, the image reading sensitivity is set higher (charge accumulating period is set longer) for a larger row number (upward in FIG. 4), and lower (charge accumulating period is set shorter) for a smaller row number (downward in FIG. 4). In FIG. 4, as the row number increases (upward in FIG. 4), the ridge/valley pattern of the fingerprint becomes weaker under the influence of external light, and at last is read as an almost

invisibly bright image. On the other hand, as the row
number decreases (downward in FIG. 4), the ridge/valley
pattern of the fingerprint becomes darker, and at last
is read as an almost invisibly dark image. The

5   lightness data level is expressed by 256 gray levels,
and its lower and upper limit values are set to 0 and
255, respectively.

In this image data, changes in lightness data
in the 176th, 152nd, 128th, 104th, and 80th rows are

10   extracted, and plotted as shown in FIGS. 5A to 5E.
In the 176th row, as shown in FIG. 5A, the sensitivity
is set high, so that lightness data substantially
converges to the upper limit value and hardly provides
any information as image data. In the 152nd row, as

15   shown in FIG. 5B, the sensitivity is set relatively
high, lightness data reaches the upper limit value in
some columns, and all the ridge/valley (bright/dark)
patterns of image data cannot be read. To the
contrary, in the 128th row, as shown in FIG. 5C,

20   lightness data does not reach either the upper or lower
limit value on all the columns, and is distributed
between the upper and lower limit values. In the 104th
row, as shown in FIG. 5D, the sensitivity is set
relatively low, and most of lightness data is

25   distributed between the upper and lower limit values.
However, lightness data reaches the lower limit value
on some columns, and all the ridge/valley patterns of

image data cannot be read. In the 80th row, as shown
in FIG. 5E, the sensitivity is set low, so that
lightness data substantially converges to the lower
limit value and hardly provides any information as

5   image data.

Maximum and minimum values are extracted as
numerical data on the basis of changes in the lightness
data distribution of each of the respective rows shown
in FIGS. 5A to 5E, and the dynamic range is calculated

10   as the difference and listed on a table as shown in
FIG. 6A. In the 176th and 152nd rows, lightness data
reaches the upper limit. Since the maximum value is
fixed to 255, the dynamic range depends on the minimum
value. In the 104th and 80th rows, lightness data

15   reaches the lower limit. Since the minimum value is
fixed to 0, the dynamic range depends on the maximum
value. In contrast, in the 128th row, lightness data
does not reach either the upper or lower limit, and
thus the dynamic range depends on the difference

20   between the maximum and minimum values of the lightness
data. The 128th row can attain the largest dynamic
range, compared to the 176th, 152nd, 104th, and 80th
rows. In other words, it can be determined that
lightness data in the 128th row is image data having

25   a fine contrast corresponding to the ridge/valley
pattern of a fingerprint, and an optimal image reading
sensitivity is set.

The RAM 130 stores the row number vs. image
reading sensitivity correspondence table shown in
FIG. 6B, and stores image reading sensitivities, i.e.,
charge accumulating periods T_1 to T_{256} for respective

5   row numbers.

The row number vs. image reading sensitivity
correspondence table is looked up for the 128th row
having the maximum dynamic range, thereby obtaining an
image reading sensitivity, i.e., charge accumulating

10   period T_{128} set for the 128th row.

If a subject (fingerprint) image is read using the
obtained charge accumulating period T_{128}, the image can
be satisfactorily read.

The first embodiment has exemplified only the

15   176th, 152nd, 128th, 104th, and 80th rows as rows
subjected to extraction and calculation processes of
the dynamic range of lightness data. As a matter of
course, the same processes can be executed for all 256
rows. When extraction and calculation processes of the

20   dynamic range of lightness data are performed not for
all the rows but for only selected specific rows, like
this embodiment, the number of data to be processed can
be decreased to simplify processing and shorten the
time required for sensitivity setting processing, and

25   the operation can quickly shift to normal reading
operation of a subject image.

A modification of the first embodiment will be

described with reference to FIGS. 7, 8A to 8E, 9A, and 9B. FIG. 7 is a view showing another example of fingerprint image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIGS. 8A to 8E are graphs each showing changes in lightness data in the column range of a specific region in several rows that are based on the subject image data obtained by the sensitivity-adjusting reading operation. FIGS. 9A and 9B are tables showing the relationship between the dynamic range of lightness data of each row that is obtained by the sensitivity-adjusting reading operation, and a row number vs. image reading sensitivity correspondence table. In this modification, unlike the first embodiment, lightness data of each row used to extract maximum and minimum values is limited to the column range of a specific region, and maximum and minimum values in this column range are extracted.

More specifically, in reading the ridge/valley pattern of a fingerprint as a subject image, the peripheral portion of a finger (region representing the edge of a finger in FIG. 7) touches an image reading surface weaker than the center of the finger. In addition, the ridge/valley pattern of the peripheral portion is not clear, and is influenced by external

factors such as external light incident via the
semitransparent layer of a skin surface layer. This
degrades the uniformity and relevance of image data.
To prevent this, the modification processes lightness
data limited to a column range around the center of
a finger which is relatively hardly influenced by
external factors and has a clear ridge/valley pattern,
thereby achieving appropriate extraction processing of
maximum and minimum values.

As shown in FIG. 7, the reading sensitivity of a
subject image is set higher (charge accumulating period
is set longer) for a larger row number. For example,
changes in lightness data in a predetermined column
range (85th column to 112th column) in the 176th,
152nd, 128th, 104th, and 80th rows are extracted
and plotted as shown in FIGS. 8A to 8E. Similar to
FIGS. 5A to 5E described above, only in the 128t row,
lightness data does not reach either the upper or lower
limit value in the entire column range partially
limited, and is distributed between the upper and lower
limit values. In the remaining rows, lightness data
reaches the upper or lower limit value, and all the
ridge/valley patterns of image data cannot be read.

FIG. 9A shows the results of extracting maximum
and minimum values as numerical data on the basis of
changes in lightness data distribution of each row,
and calculating the dynamic range from the difference.

It can be determined that the dynamic range of
lightness data in the 128th row is maximum, and that
image data having a fine contrast corresponding to the
ridge/valley pattern of a fingerprint is obtained.

5 That is, an optimal image reading sensitivity can be
determined to be set.

As shown in FIG. 6B, the row number vs. image
reading sensitivity correspondence table stored in the
RAM 130 stores charge accumulating periods T_1 to T_{256}

10 for respective row numbers. As shown in FIG. 9B, the
row number vs. image reading sensitivity correspondence
table is looked up for the 128th row having the maximum
dynamic range, thereby attaining an image reading
sensitivity set for the 128th row, i.e., charge

15 accumulating period T_{128} of the double-gate
photosensor.

The sensitivity setting method of this modifica-
tion can determine a row in an optimal image reading
state on the basis of the dynamic range of lightness

20 data in a predetermined column range for each row in
setting an optimal image reading sensitivity based on
the results of sensitivity-adjusting reading operation.
Accordingly, the data amount to be processed can be
decreased to simplify sensitivity setting processing

25 and shorten the required time.

<Second Embodiment>

The second embodiment of a photosensor system

drive control method to which the same controller 120 as in the first embodiment can be applied will be described with reference to the several views of the accompanying drawing.

5   FIG. 10 is a flow chart showing an operation up to read of a subject image with an optimal sensitivity according to the second embodiment in operation control of the photosensor system. This operation will be described by properly referring to the arrangement of

10   the photosensor system shown in FIGS. 1 and 2.

In S21 (sensitivity-adjusting reading operation) of FIG. 10, a main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in a sensitivity setting register 127

15   via a data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise for respective rows of the subject image. These

20   operations are executed prior to normal reading operation of a subject image, for example. The image reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspon- dence table in a RAM 130 in correspondence with row

25   numbers. This sensitivity-adjusting reading operation is the same as the operation in the first embodiment, and a detailed method of setting the image reading

sensitivity (charge accumulating period) will be described below.

In S22 (image data conversion step) of FIG. 10, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via an amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to a data comparator 124. In this case, the lightness data is expressed by, e.g., 256 gray levels.

In S23 (data extraction step in the column direction) of FIG. 10, the data comparator 124 extracts lightness data on a specific column, and outputs it to an adder 125.

In S24 (differentiation processing step in the column direction) of FIG. 10, the adder 125 calculates the displacement (differentiated value) of each row in the column direction of the extracted luminance data, and stores the displacement in the RAM 130.

In S25 (step of extracting a row number having the maximum differentiated value) of FIG. 10, the differentiated values of lightness data stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number having the maximum differentiated value among the differentiated values of lightness data.

In S26 (sensitivity referring/extraction step) of

FIG. 10, the row number vs. image reading sensitivity

correspondence table stored in the RAM 130 is referred

based on the row number having the maximum differenti-

ated value, and an image reading sensitivity, i.e.,

5   charge accumulating period set for this row is

extracted.

In S27 (extracted sensitivity setting step) of

FIG. 10, the data controller 122 rewrites the

sensitivity setting register 127 to set the image

10   reading sensitivity in the sensitivity setting register

127 to the extracted image reading sensitivity. In S28

(subject image reading step) of FIG. 10, normal reading

operation of a subject image is executed at the

extracted image reading sensitivity set in the

15   sensitivity setting register 127.

An example of applying the second embodiment

of the photosensor system drive control method to

a fingerprint reading apparatus will be described with

reference to FIGS. 11 to 13B.

20   FIG. 11 is a view showing an example of

fingerprint image data when a subject (fingerprint)

image is read while the image reading sensitivity is

changed stepwise for respective rows in sensitivity-

adjusting reading operation. FIGS. 12A and 12B are

25   graphs, respectively, showing the value of lightness

data in a predetermined column that is obtained by the

sensitivity-adjusting reading operation, and the

displacement (differentiated value) of lightness data between rows. FIGS. 13A and 13B are tables showing the relationship between the displacement of lightness data between rows in a predetermined column that is obtained by the sensitivity-adjusting reading operation, and a row number vs. image reading sensitivity correspondence table. Assume that image data is read out in units of a matrix pattern of 256 rows $\times$ 196 columns. A larger lightness data value represents a brighter image, and a smaller lightness data value represents a darker image.

In the sensitivity-adjusting reading operation, the image reading sensitivity is set higher (charge accumulating period is set longer) for a larger row number (upward in FIG. 11), and lower (charge accumulating period is set shorter) for a smaller row number (downward in FIG. 11). For example, lightness data of respective rows (1st to 256th rows) on the 98th column are extracted and plotted as shown in FIG. 12A.

In a region having a small row number, the image reading sensitivity is set low, and lightness data converges to the lower limit value. In a region having a large row number, the image reading sensitivity is set high, and lightness data converges to the upper limit value. To the contrary, in a region around the central row (128th row), lightness data does not reach either the upper or lower limit value, and is

distributed between the upper and lower limit values.
Further, lightness data tends to change from the lower
limit value to the upper limit value.

Differentiated values representing the
displacements of lightness data of respective rows are
calculated based on changes in lightness data of these
rows, and plotted to obtain a distribution as shown in
FIG. 12B. The distribution of the differentiated value
of lightness data shown in FIG. 12B is listed on
a table as shown in FIG. 13A. From this table, the
differentiated value is observed to maximize between
the 125th and 126th rows, and image data having a fine
contrast corresponding to the ridge/valley pattern of
the fingerprint is determined to be obtained. That is,
an optimal image reading sensitivity can be determined
to be set.

Similar to the table shown in FIG. 6B, the row
number vs. image reading sensitivity correspondence
table stored in the RAM 130 stores charge accumulating
periods T_1 to T_{256} for respective row numbers. This
table is looked up for the 125th and 126th rows having
the maximum differentiated value to acquire image
reading sensitivities set for the 125th and 126th rows,
i.e., charge accumulating periods T_{125} and T_{126} of the
photosensor. The sensitivity setting register is
rewritten to set a set value determined based on the
two charge accumulating periods T_{125} and T_{126}, i.e.,

the average of the charge accumulating periods T_{125} and T_{126}. A subject (fingerprint) image is read at this optimal image reading sensitivity.

Similar to the modification of the first embodiment, the column number of lightness data to be processed is desirably specified to a column around the central portion of a subject (finger) which is relatively hardly influenced by external factors and at which the bright/dark pattern (ridge/valley pattern) of a subject image can be read clearly.

In setting an optimal image reading sensitivity based on the results of sensitivity-adjusting reading operation, the sensitivity setting method of the second embodiment can easily determine a row in an optimal image reading state on the basis of the displacement of lightness data of each row in a specific column, and can set an image reading sensitivity (charge accumulating period) set for this row as an optimal sensitivity. Lightness data to be processed suffices to be one column (i.e., several rows), and data to be processed in sensitivity setting processing can be greatly decreased to further simplify sensitivity setting processing and shorten the required time.

<Third Embodiment>

The third embodiment of a photosensor system drive control method according to the present invention will be described with reference to the several views of the

accompanying drawings.

The arrangement of a controller applied to the third embodiment has the same arrangement block as the controller 120 employed in the first and second embodiments shown in FIG. 2. In addition, an adder 125 calculates a dynamic range from the difference between the maximum and minimum values of measurement data, and calculates the difference between respective dynamic ranges, i.e., linearly differentiated value. A data comparator 124 has a function of extracting the maximum value of a dynamic range calculated by the adder 125, and the minimum or maximum value of the difference (linearly differentiated value) between dynamic ranges.

FIG. 14 is a flow chart showing an operation up to read of a subject image with an optimal sensitivity according to the third embodiment in the photosensor system operation control method using the above controller 120. This operation will be described by properly referring to the arrangement of the photosensor system shown in FIGS. 1 and 2.

In S31 (sensitivity-adjusting reading operation) of FIG. 14, a main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in a sensitivity setting register 127 via a data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities

while changing the image reading sensitivity stepwise
for respective rows of the subject image. These
operations are executed prior to normal reading
operation of a subject image, for example. The image

5   reading sensitivities of respective rows are stored
as a row number vs. image reading sensitivity
correspondence table in a RAM 130 in correspondence
with row numbers. This sensitivity-adjusting reading
operation is the same as the operation in the first

10   embodiment, and a detailed method of setting the image
reading sensitivity (charge accumulating period) will
be described below.

In S32 (image data conversion step) of FIG. 14,
the image data read by the sensitivity-adjusting

15   reading operation is converted into a digital signal
via an amplifier 116 and A/D converter 117, and input
as lightness data corresponding to the bright/dark
pattern of the subject image to a data comparator 124.
In this case, the lightness data is expressed by, e.g.,

20   256 gray levels.

In S33 (step of extracting the maximum and minimum
values of each row) of FIG. 14, the data comparator 124
extracts the maximum and minimum values of lightness
data of each row, and outputs them to an adder 125.

25   That is, the data comparator 124 extracts lightness
data representing a maximum value (gray level value of
the brightest pixel) contained in each row, and

lightness data representing a minimum value (gray level value of the darkest pixel).

In S34 (step of calculating the dynamic range of each row) of FIG. 14, the adder 125 calculates as a dynamic range the difference between the maximum and minimum values of lightness data of each row, and stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range calculation processing for all the rows.

In S35 (step of calculating the linearly differentiated value of the dynamic range) of FIG. 14, the dynamic ranges of respective rows stored in the RAM 130 are read out via the data selector 126, and input again to the adder 125, which calculates the difference (linearly differentiated value) between the dynamic ranges of adjacent rows. The results are stored in the RAM 130 via the data selector 126.

In S36 (step of extracting a row number having a maximum dynamic range and minimum linearly differentiated value) of FIG. 14, data of the dynamic ranges of respective rows and data of the linearly differentiated values of the dynamic ranges which are stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number at which the dynamic range maximizes and the linearly differentiated value of the dynamic range minimizes (to 0 or a value close to 0).

In S37 (sensitivity referring/extraction step) of FIG. 14, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is looked up based on the extracted row number, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

In S38 (extracted sensitivity setting step) of FIG. 14, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity. In S39 (subject image reading step) of FIG. 14, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the third embodiment of the photosensor system drive control method to a fingerprint reading apparatus will be described with reference to FIGS. 15 to 18B.

FIG. 15 is a view showing an example of image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIG. 16 is a graph showing changes in lightness data of respective pixels of several rows in the column direction that are based on the subject image data obtained by the sensitivity-adjusting

reading operation. FIGS. 17A and 17B are graphs
showing the relationship between changes in the dynamic
ranges of respective rows and changes in the linearly
differentiated values of the dynamic ranges of
5   respective rows. FIGS. 18A and 18B are views for
illustrating tables showing the relationship between
the dynamic range of each row and the linearly
differentiated values of the dynamic range that are
obtained by the sensitivity-adjusting reading
10   operation, and a row number vs. image reading
sensitivity correspondence table. Assume that image
data are read out in units of a matrix pattern of 256
rows × 196 columns. A larger lightness data value
represents a brighter image, and a smaller lightness
15   data value represents a darker image.

In the sensitivity-adjusting reading operation,
the image reading sensitivity is set higher (charge
accumulating period is set longer) for a larger row
number (upward in FIG. 15), and lower (charge
20   accumulating period is set shorter) for a smaller row
number (downward in FIG. 15). In FIG. 15, as the row
number increases (upward in FIG. 15), the ridge/valley
pattern of the fingerprint becomes weaker under the
influence of external light, and at last is read as an
25   almost invisibly bright image. On the other hand, as
the row number decreases (downward in FIG. 15), the
ridge/ valley pattern of the fingerprint becomes

darker, and at last is read as an almost invisibly dark image. The lightness data level is expressed by 256 gray levels, and its lower and upper limit values are set to 0 and 255, respectively.

In this image data, a sensitivity determination range used to extract a row having an optimal sensitivity is preferably limited to a region having a fine contrast corresponding to the ridge/valley pattern of the fingerprint. This embodiment will exemplify sensitivity setting processing when a row/column range defined by 64th to 191st rows and 67th to 130th columns is set as the sensitivity determination range.

In the sensitivity determination range shown in FIG. 15, for example, changes in lightness data in the 64th, 96th, 160th, and 191st rows are extracted and plotted as shown in FIG. 16. In the 191st row (represented by the broken line in FIG. 16) and 160th row (represented by the thin line in FIG. 16) within the row range, the sensitivity is set high, and lightness data converges to a large value (about 220 to 225) and hardly provides any information as image data. In the 96th row (represented by the thick line in FIG. 16), lightness data does not converge to either the upper or lower limit value on all the columns, and exhibits a relatively large vertical displacement corresponding to the bright/dark pattern of image data. In the 64th row (represented by the chain line in

FIG. 16), the sensitivity is set low, so that lightness data converges to a small value (about 35) and hardly provides any information as image data.

Maximum and minimum values are extracted from the lightness data distribution of each row, and the difference is calculated to obtain a dynamic range. Obtained dynamic ranges are plotted for row numbers to attain a distribution curve having a maximum value MA in a predetermined row, as shown in FIG. 17A. Further, linear differentiation for the dynamic range distribution, i.e., the slopes of the dynamic range distribution curve for respective rows are calculated, and plotted for row numbers. As shown in FIG. 17B, a linearly differentiated value MB is 0 in a row exhibiting the maximum value MA.

It can be determined that lightness data in the row exhibiting the maximum dynamic range and minimum linearly differentiated value is image data having a fine contrast corresponding to the ridge/valley pattern of a fingerprint, and an optimal image reading sensitivity is set.

Maximum and minimum values are extracted as numerical data on the basis of changes in the lightness data distribution of each row shown in FIG. 16, and a dynamic range calculated from the difference and a linearly differentiated value calculated from the difference of the dynamic range of each row are listed

on a table as shown in FIG. 18A.

In FIG. 18A, when the dynamic range maximizes at R_k in FIG. 18A, and the linearly differentiated value minimizes at D_{k-1} in FIG. 18A, rows L_{k-1} and L_k are

5   extracted as row numbers at which the dynamic range maximizes and the linearly differentiated value minimizes.

As shown in FIG. 6B, the RAM 130 stores a row number vs. image reading sensitivity correspondence

10   table within the sensitivity determination range, and stores image reading sensitivities, i.e., charge accumulating periods T_{64} to T_{191} for respective row numbers.

This row number vs. image reading sensitivity

15   correspondence table is looked up for the extracted rows to extract image reading sensitivities, i.e., charge accumulating periods T_{k-1} and T_k set for the rows L_{k-1} and L_k, which are determined as optimal values. The sensitivity setting register 127 is

20   rewritten to set, as an optimal image reading sensitivity, a set value determined based on the two extracted charge accumulating periods T_{k-1} and T_k, i.e., the average of the charge accumulating periods T_{k-1} and T_k. A subject (fingerprint) image is read at

25   this optimal image reading sensitivity.

Note that in the distributions of the dynamic range and linearly differentiated value shown in

FIGS. 17A and 17B, the linearly differentiated value of a row whose dynamic range has the maximum value MA is 0. In practice, however, a row whose linearly differentiated value is 0 may not exist. Thus, as conditions for extracting a row set to an optimal sensitivity, a row exhibiting the maximum dynamic range and the minimum linearly differentiated value (value nearest to 0) is extracted.

As will be described below, the third embodiment can effectively prevent any malfunction in optimal sensitivity extraction processing even when lightness data contains an abnormal value due to a small foreign substance attached to the fingerprint reading surface of the photosensor, a defect of the photosensor, or the like. This will be explained with reference to FIGS. 19A to 22B.

FIGS. 19A and 19B are tables showing the relationship between the dynamic range distribution of respective rows and a row number vs. image reading sensitivity correspondence table when the first embodiment is applied as another setting method of setting the optimal sensitivity of the photosensor system. According to this setting method, the optimal value of the image reading sensitivity is determined using a row whose dynamic range has the maximum value MA in the dynamic range distribution (see FIG. 17A) of lightness data in sensitivity setting processing

described above.

In this sensitivity setting method, as described above, the dynamic range is calculated based on the lightness data distribution (maximum and minimum values) of each row in FIG. 19A, a row (L_k in FIG. 19A) having the maximum value (e.g., R_k in FIG. 19A) is extracted, and an image reading sensitivity (charge accumulating period T_k) set for the row L_k is extracted and determined as an optimal value.

Operation processing when lightness data contains an abnormal value, and comparison with the third embodiment will be explained.

FIG. 20 is a view showing still another example of image data when a subject (fingerprint) image is read while the image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIG. 21 is a graph showing changes in the dynamic ranges of respective rows. FIGS. 22A and 22B are graphs showing the relationship between changes in the dynamic ranges of respective rows, and changes in the linearly differentiated values of the dynamic ranges of respective rows.

As shown in FIG. 20, the sensitivity determination range is set to a row/column range defined by 64th to 191st rows and 67th to 130th columns, similar to FIG. 15, as a region having a fine contrast correspond-ing to the ridge/valley pattern of a fingerprint in

- 50 -

order to extract a row having an optimal sensitivity
from image data of the fingerprint. In this case, if
an abnormal pixel IL1 exists in a row L within the
sensitivity determination range owing to a foreign
5   substance attached to a fingerprint reading surface,
a defect of the photosensor, or the like, lightness
data of the abnormal pixel IL1 may exhibit an excessive
value in comparison with peripheral pixel data.
This occurs when, for example, a black point exists on
10   the white background, or a white point exists on the
black background. In the distribution of a dynamic
range calculated based on the maximum and minimum
values of lightness data, the dynamic range of the row
L containing the abnormal pixel IL1 appears greatly
15   apart from the change trend of the entire distribution.
If the setting method of the first embodiment in which
an image reading sensitivity corresponding to a row
having the maximum dynamic range is adopted as
an optimal value is applied to image data read in the
20   sensitivity-adjusting reading operation, the dynamic
range of the row L containing the abnormal pixel IL1
that is irrelevant to an original maximum value MA1 in
the change trend of the dynamic range distribution is
extracted as a maximum value MA2, and an image reading
25   sensitivity set for the row L having this dynamic range
is determined to be an optimal value. In this case, an
improper image reading sensitivity (e.g., charge

accumulating period longer than an optimal value) is set in the photosensor system. In normal reading operation, accurate reading operation may fail such that a subject image becomes white.

To the contrary, the sensitivity setting method of the third embodiment sets an optimal image reading sensitivity using conditions of extracting a row number at which the dynamic range exhibits the maximum value MA1 and the linearly differentiated value of the dynamic range exhibits a minimum value MB1 within a range where the dynamic range coincides with the entire dynamic range change trend. For this reason, the third embodiment does not extract, as a row corresponding to an optimal reading sensitivity, the row L containing the abnormal pixel IL1 in which a dynamic range value MA2 in FIG. 22A deviates from the dynamic range change trend and is a maximum value, but a linearly differentiated value MB2 of the dynamic range in FIG. 22B is not a minimum value.

Hence, even when a subject image contains the abnormal pixel IL1 due to a foreign substance attached to a fingerprint reading surface, a defect of the photosensor, or the like, a row having a fine contrast corresponding to the ridge/valley pattern of a fingerprint can be reliably extracted to determine an optimal charge accumulating period.

According to the sensitivity setting method of the

third embodiment, sensitivity-adjusting reading operation is executed while the image reading sensitivity is changed stepwise for respective rows. A row in an optimal image reading state is easily and

5   properly determined based on the dynamic range value of each row to lightness data and the linearly differentiated value of the dynamic range. An image reading sensitivity (charge accumulating period) set for the row can be set as an optimal sensitivity.

10   Normal image reading operation of a subject image can be performed at a proper sensitivity without being influenced by an abnormal pixel generated by a foreign substance attached to a fingerprint reading surface, a defect of the photosensor, or the like.

15   The third embodiment executes sensitivity setting processing in a sensitivity determination range limited to a row/column range defined by 64th to 191st rows and 67th to 130th columns. However, the present invention is not limited to this, and is applicable to the entire

20   region of image data without limiting the sensitivity determination range.

<Fourth Embodiment>

The fourth embodiment of a photosensor system drive control method according to the present invention

25   to which the same controller 120 as in the third embodiment can be applied will be described with reference to the several views of the accompanying

drawing.   The fourth embodiment determines whether an abnormal pixel exists in image data by applying the sensitivity setting method of the third embodiment.

FIG. 23 is a flow chart showing an operation up to detection processing of an abnormal pixel according to the fourth embodiment in the photosensor system operation control method using the above-mentioned controller 120.

In S41 (sensitivity-adjusting reading operation) of FIG. 23, a main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in a sensitivity setting register 127 via a data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise for respective rows of the subject image.   These operations are executed prior to normal reading operation of a subject image, for example.   The image reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspondence table in a RAM 130 in correspondence with row numbers.   This sensitivity-adjusting reading operation is the same as the operation in the first embodiment, and a detailed method of setting the image reading sensitivity (charge accumulating period) will be described below.

In S42 (image data conversion step) of FIG. 23, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via an amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to a data comparator 124. In this case, the lightness data is expressed by, e.g., 256 gray levels.

In S43 (step of extracting the maximum and minimum values of each row) of FIG. 23, the data comparator 124 extracts the maximum and minimum values of lightness data of each row, and outputs them to an adder 125. That is, the data comparator 124 extracts lightness data representing a maximum value (gray level value of the brightest pixel) contained in each row, and lightness data representing a minimum value (gray level value of the darkest pixel).

In S44 (step of calculating the dynamic range of each row) of FIG. 23, the adder 125 calculates as a dynamic range the difference between the maximum and minimum values of lightness data of each row, and stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range calculation processing for all the rows.

In S45 (step of calculating the linearly differentiated value of the dynamic range) of FIG. 23, the dynamic ranges of respective rows stored in the RAM

130 are read out via the data selector 126, and input again to the adder 125, which calculates the difference (linearly differentiated value) between the dynamic ranges of adjacent rows. The results are stored in the RAM 130 via the data selector 126.

In S46 (step of extracting a row number having a maximum dynamic range and maximum linearly differentiated value) of FIG. 23, data of the dynamic ranges of respective rows and data of the linearly differentiated values of the dynamic ranges which are stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number at which the dynamic range maximizes and the linearly differentiated value of the dynamic range maximizes.

In S47 (step of determining presence/absence of an extracted row) of FIG. 23, whether a corresponding row number has been extracted in step S46, i.e., whether a row which satisfies extraction conditions exists is determined. If a corresponding row number is determined based on the determination result to have been extracted, an abnormal pixel is determined to exist in the image data read by the sensitivity-adjusting reading operation. If no corresponding row number is determined to have been extracted, no abnormal pixel is determined to exist.

This abnormal pixel detection processing can

determine the presence/absence of a foreign substance
attached to the read surface for a subject or the
subject itself, or the presence/absence of a defect of
the sensor element constituting the photosensor array.
If an abnormal pixel exists, this can be notified with
an alarm or the like to execute proper action, and
normal reading operation of a subject image can be
appropriately done in S48.

More specifically, as shown in FIG. 20, a prede-
termined sensitivity determination range is set on
image data of a fingerprint. At this time, if
the abnormal pixel IL1 exists in the sensitivity
determination range due to a foreign substance attached
to a fingerprint reading surface, characteristic
changes and defects of the photosensor, or the like,
lightness data of the abnormal pixel IL1 exhibits an
excessive value in comparison with peripheral pixel
data. In this case, a dynamic range calculated based
on the maximum and minimum values of this lightness
data, and its linearly differentiated value appear
greatly apart from the remaining normal distribution
trend, as shown in FIGS. 21, 22A, and 22B. When the
abnormal detection method of the fourth embodiment is
applied to this situation, a row number L at which the
dynamic range exhibits the maximum value MA2 and the
linearly differentiated value of the dynamic range
exhibits the maximum value MB2 is extracted to

determine that the abnormal pixel IL1 exists in the
image data. As a result, proper action of, e.g.,
cleaning the sensing surface to remove the foreign
substance can be instructed prior to normal reading

5   operation of a subject image.

Note that the abnormal detection method of
the fourth embodiment may be executed singly for
a predetermined subject image, or may be executed in
parallel with the above-described sensitivity setting

10   method.

<Fifth Embodiment>

The fifth embodiment of a photosensor system drive
control method according to the present invention will
be described with reference to the several views of the

15   accompanying drawing.

The detailed arrangement and operation of a
controller applied to the fifth embodiment will be
explained with reference to the several views of the
accompanying drawing.

20   FIG. 24 is a block diagram showing an arrangement
of the controller 120a applied to this embodiment. As
will be described below, this controller 120a has
almost the same arrangement as the controller 120 shown
in FIG. 2, and the same reference numerals denote the

25   same parts.

As shown in FIG. 24, a controller 120a in the
fifth embodiment comprises a device controller 121 for

controlling a top gate driver 111, bottom gate driver 112, and output circuit section 113, a data controller 122 for managing various data such as image data, write data, and readout data to a RAM 130, and a main controller 123 which supervises the controllers 121 and 122 and interfaces with an external function section.

The controller 120a further comprises:

an abnormal value removing section 128 constituted by a Fourier transformation section or circuit 128a for Fourier-transforming specific measurement data based on image data input as a digital signal from a photosensor array 100 via an A/D converter 117, a filtering section or circuit 128b for removing a high-frequency component corresponding to an abnormal value from the Fourier-transformed measurement data, and an inverse Fourier transformation section or circuit 128c for inversely Fourier-transforming the measurement data from which the high-frequency component is removed;

a data comparator 124 for extracting maximum and minimum values by comparing the sizes of measurement data from which abnormal values are removed by the abnormal value removing section 128, and for extracting the maximum value of a dynamic range calculated by an adder 125 (to be described below) and the minimum value of the difference (linearly differentiated value) between dynamic ranges;

the adder 125 for calculating a dynamic range from

the difference between the maximum and minimum values of measurement data, and calculating the difference between dynamic ranges, i.e., linearly differentiated value;

5   a data selector 126 for receiving measurement data processed via the A/D converter 117, abnormal value removing section 128, data comparator 124, and adder 125, and switching write/readout in/from the RAM 130, re-input to the data comparator 124 and adder 125, and

10   output to the external function section 200 via the data controller 122 in accordance with the received data; and

        a sensitivity setting register 127 for changing control signals to be output from the device controller

15   121 to the top and bottom gate drivers 111 and 112 so as to optimize the reading sensitivity of the photosensor array on the basis of a control signal from the data controller 122.

        The operation of the fifth embodiment in the

20   operation control method of the photosensor system using the above controller 120a will be explained with reference to FIG. 25. FIG. 25 is a flow chart showing an operation up to read of a subject image with an optimal sensitivity according to the fifth embodiment

25   in operation control of the photosensor system. This operation will be described by properly referring to the arrangement of the photosensor system shown in

FIGS. 1 and 24.

In S51 (sensitivity-adjusting reading operation) of FIG. 25, the main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in the sensitivity setting register 127 via the data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise for respective rows of the subject image. The image reading sensitivities of respective rows are stored as a row number vs. image reading sensitivity correspondence table in the RAM 130 in correspondence with row numbers. This sensitivity-adjusting reading operation is the same as the operation in the first embodiment, and a detailed method of setting the image reading sensitivity (charge accumulating period) will be described below.

In S52 (image data conversion step) of FIG. 25, the image data read by the sensitivity-adjusting reading operation is converted into a digital signal via the amplifier 116 and A/D converter 117, and input as lightness data corresponding to the bright/dark pattern of the subject image to the abnormal value removing section 128. In this case, the lightness data is expressed by, e.g., 256 gray levels.

In S53 (Fourier transformation step) of FIG. 25,

the lightness data input to the abnormal value removing
section 128 is Fourier-transformed by the Fourier
transformation section 128a on the basis of the
dynamic range of lightness data of each row to obtain

5   a frequency distribution representing the variation
width of lightness data of each row number.

In S54 (high-frequency component removing step)
of FIG. 25, a high-frequency component equal to or
higher than a predetermined value is removed from

10   the lightness data frequency distribution converted
by the Fourier transformation section 128a. More
specifically, a predetermined high-frequency component
is removed by passing the data through the filtering
section 128b formed from, e.g., a low-pass filter.

15   In S55 (inverse Fourier transformation step) of
FIG. 25, the frequency distribution from which the
high-frequency component is removed is inversely
Fourier-transformed by the inverse Fourier transforma-
tion section 128c to obtain lightness data of each row

20   number again.

A series of abnormal value removing operations of
the abnormal value removing section 128 remove from
original lightness data a high-frequency component,
i.e., abnormal value which has a steep variation and

25   deviates from the main change trend of lightness data,
and extract only the main component of the lightness
data in which the dynamic range changes smoothly for

each row. The lightness data from which the abnormal value is removed is input to the data comparator 124.

In S56 (step of extracting the maximum and minimum values of each row) of FIG. 25, the data comparator 124 extracts for each row the maximum and minimum values of the lightness data from which the abnormal value is removed, and outputs them to the adder 125. That is, the data comparator 124 extracts lightness data representing a maximum value (gray level value of the brightest pixel) contained in each row, and lightness data representing a minimum value (gray level value of the darkest pixel).

In S57 (step of calculating the dynamic range of each row) of FIG. 25, the adder 125 calculates as a dynamic range the difference between the maximum and minimum values of lightness data of each row, and temporarily stores the dynamic range in the RAM 130 via the data selector 126. The adder 125 executes dynamic range calculation processing for all the rows.

In S58 (step of calculating the linearly differentiated value of the dynamic range) of FIG. 25, the dynamic ranges of respective rows stored in the RAM 130 are read out via the data selector 126, and input again to the adder 125, which calculates the difference (linearly differentiated value) between the dynamic ranges of adjacent rows. The results are stored in the RAM 130 via the data selector 126.

In S59 (step of extracting a row number having a maximum dynamic range and minimum linearly differentiated value) of FIG. 25, data of the dynamic ranges of respective rows and data of the linearly differentiated values of the dynamic ranges which are stored in the RAM 130 are read out via the data selector 126, and input to the data comparator 124, which extracts a row number at which the dynamic range maximizes and the linearly differentiated value of the dynamic range minimizes (to 0 or a value close to 0).

In S60 (sensitivity referring/extraction step) of FIG. 25, the row number vs. image reading sensitivity correspondence table stored in the RAM 130 is looked up based on the extracted row number, and an image reading sensitivity, i.e., charge accumulating period set for this row is extracted.

In S61 (extracted sensitivity setting step) of FIG. 25, the data controller 122 rewrites the sensitivity setting register 127 to set the image reading sensitivity in the sensitivity setting register 127 to the extracted image reading sensitivity. In S62 (subject image reading step) of FIG. 25, normal reading operation of a subject image is executed at the extracted image reading sensitivity set in the sensitivity setting register 127.

An example of applying the fifth embodiment of the photosensor system drive control method to a

fingerprint reading apparatus will be described with reference to FIGS. 26 to 27B.

As will be described below, the fifth embodiment can effectively prevent any malfunction in optimal sensitivity extraction processing even when image data read by the sensitivity-adjusting reading operation contains an abnormal value, and the abnormal value exists on not only one pixel but across a plurality of pixels. This embodiment can also be effectively applied to a case wherein image data does not contain any abnormal value, which will be described first.

The sensitivity-adjusting reading operation in the fifth embodiment is the same as that in the above embodiments. The fifth embodiment will exemplify a case wherein image data read by the sensitivity-adjusting reading operation is the same as image data shown in FIG. 15, and the sensitivity determination range is defined to a row/column range of 64th to 191st rows and 67th to 130th columns.

The result of extracting changes in lightness data in the 64th, 96th, 160th, and 191st rows in the sensitivity determination range and plotting them is the same as FIG. 16.

In accordance with the above-mentioned abnormal value removing operation, the lightness data distribution of respective rows is Fourier-transformed to obtain a frequency distribution for the row number,

a high-frequency component corresponding to an abnormal value or noise is removed, and the resultant data is inversely Fourier-transformed to extract only lightness data representing a main change trend in the lightness data distribution of respective rows. In this case, image data does not contain any abnormal value. Thus, even if the high-frequency component of lightness data is removed, the lightness data distribution trend does not especially change. Hence, the dynamic range distribution of respective rows is the same as that shown in FIG. 17A. Changes in the linearly differentiated values of respective rows to this dynamic range distribution are also the same as those shown in FIG. 17B. For this reason, a row number extracted under conditions that the dynamic range is maximum and the linearly differentiated value is minimum is the same as in the third embodiment, and an optimal image reading sensitivity based on the extracted row number is also the same as in the third embodiment.

The following description concerns sensitivity setting operation when image data contains an abnormal value owing to a foreign substance attached to a subject or the sensing surface of the photosensor array, a defect of the sensor element constituting the photosensor array, or the like.

FIG. 26 is a view showing an example of image data when a subject (fingerprint) image is read while the

image reading sensitivity is changed stepwise for respective rows in sensitivity-adjusting reading operation. FIG. 27A is a graph showing the dynamic range distribution of lightness data of respective rows when a subject image has a component corresponding to a foreign substance or the like. FIG. 27B is a graph showing the dynamic range distribution of lightness data of respective rows after abnormal value removing operation according to the fifth embodiment.

As shown in FIG. 26, similar to the above-described case, a row/column range of 64th to 191st rows and 67th to 130th columns is set as a sensitivity determination range for read fingerprint image data. In this case, if an abnormal pixel IL2 relatively large enough to overlap a plurality of rows (LA to LB rows) exists in the sensitivity determination range owing to a foreign substance attached to the sensing surface of the photosensor array, a defect of the photosensor element, noise contained in image data, or the like, the lightness data of the abnormal pixel IL2 may exhibit an excessive value in a plurality of rows in comparison with peripheral pixel data, i.e., a value deviating from the change trend of peripheral pixel data. This occurs when, e.g., a relatively large black point exists on the white background, or a relatively large white point exists on the black background, and more specifically, when the variation width or dynamic

range of lightness data discretely varies in respective rows, or abnormal pixel data MC due to a foreign substance attached to the sensing surface or a defect of an element exists across a plurality of rows (LA to

5   LB rows), as shown in FIG. 27A.

If the sensitivity setting method of the third embodiment is applied without performing abnormal value removing operation, this sensitivity setting method extracts a row in which the dynamic range of lightness

10   data for each row is maximal and the linearly differentiated value is minimal as a row having an optimal image reading sensitivity. Thus, the dynamic ranges of rows on which the abnormal pixel IL2 continuously exists may be recognized to exhibit a

15   maximum value with respect to the main distribution trend of the whole dynamic range. In addition, the linearly differentiated value in a region representing a continuous change exhibits a value close to 0, and may be recognized to be a minimum value. As a result,

20   a row (row between LA and LB) containing the abnormal pixel IL2 irrelevant to a row having an original optimal image reading sensitivity may be mistaken as a row corresponding to an optimal image reading sensitivity. In this case, an improper image reading

25   sensitivity (e.g., charge accumulating period longer than an optimal value) is set in the photosensor system. In normal reading operation, a subject image

may become, e.g., white.

To the contrary, the sensitivity setting method of the fifth embodiment can remove any abnormal value contained in lightness data by performing Fourier transformation to remove a high-frequency component corresponding to an abnormal value or noise prior to processing of obtaining the optimal value of the reading sensitivity based on the dynamic range of lightness data. As shown in FIG. 27B, an abnormal value greatly deviating from the dynamic range distribution trend of lightness data for the row number is eliminated, and only smoothed lightness data MD representing a main change trend is extracted. On the basis of the extracted lightness data MD, a row corresponding to a maximum value MA3 of the dynamic range shown in FIG. 27B is extracted as a row having an optimal image reading sensitivity under the conditions that the dynamic range is maximum and the linearly differentiated value of the dynamic range is minimum.

Even when a subject image contains the abnormal pixel IL2 relatively large enough to overlap a plurality of rows owing to a foreign substance attached to the sensing surface of the photosensor array, a defect of the photosensor element, noise contained in image data, or the like, a row having a fine contrast corresponding to the ridge/valley pattern of a fingerprint can be reliably extracted to determine

an optimal charge accumulating period. The fifth

embodiment can therefore provide a fingerprint reading

apparatus capable of reading a high-quality fingerprint

image with almost no malfunction.

5   Note that the fifth embodiment executes

sensitivity setting processing while the sensitivity

determination range is limited to a row/column range of

64th to 191st rows and 67th to 130th columns. However,

the embodiment is not limited to this, and can also be

10   applied to a case wherein sensitivity setting

processing is executed for the entire region of image

data without limiting the sensitivity determination

range.

<Sixth Embodiment>

15   The sixth embodiment of a photosensor system drive

control method according to the present invention will

be described with reference to the accompanying

drawings.

In the first to fifth embodiments described above,

20   the sensitivity-adjusting reading operation is

performed, with the image reading sensitivity being

changed stepwise for each of the rows of the

photosensor array, and one subject image is thereby

read at a plurality of different densities. In the

25   sixth embodiment, the image reading sensitivity of the

photosensors of one or several rows (hereinafter

referred to as a specific row section) of the

photosensor array is changed stepwise, and the subject image portion corresponding to the specific row section is read. The controller applied to the sixth embodiment is similar in structure to the controller 120 employed in the first and second embodiments and represented by the structural blocks shown in FIG. 2.

FIG. 28 is a flowchart illustrating how the controller 120 controls the operation of the photosensor system in the sixth embodiment of the present invention. In the flowchart, the operations executed up to the optimal image reading sensitivity setting are illustrated. FIG. 29 shows a specific row section of the photosensor array for which the sensitivity-adjusting reading operation is performed according to the sixth embodiment, the specific row section being illustrated as n/2 in relation to a subject image. In the description below, reference will be made to the structure of the photosensor system shown in FIGS. 1 and 2, if required.

In S71 (sensitivity-adjusting reading operation) of FIG. 28, the main controller 123 controls to set an image reading sensitivity for sensitivity-adjusting reading operation in the sensitivity setting register 127 via the data controller 122, and executes the sensitivity-adjusting reading operation of reading a subject image at a plurality of different sensitivities while changing the image reading sensitivity stepwise

for respective specific row section of the subject
image. These operations are executed prior to the
normal reading operation of the subject image, for
example. It should be noted that the sensitivity-
adjusting reading operation applicable to the
sensitivity adjusting method of the sixth embodiment is
performed, using a photosensor array 100 in which
photosensors are arranged in units of a matrix pattern
of 256 rows × 196 columns, as shown in FIG. 29. In
this photosensor array, a central row (i.e., the n/2-th
row) or several rows in the vicinity thereof are
regarded as a specific row section, and the
photosensors 10 corresponding to the specific row
section are reset. Thereafter, precharge operation and
readout operation are repeatedly executed at
predetermined timings in such a manner that the charge
accumulating period (image reading sensitivity) varies
stepwise. In other words, the image reading
sensitivity is made to vary in correspondence to the
number of times reading operation is executed. Data
are stored in a RAM 130 ,for example, in a table format
of (the number of times of reading operation) vs (image
reading sensitivity correspondence table). A specific
method for setting the image reading sensitivity will
be described later.

In S72 (image data conversion step) of FIG. 28,
the image data read by the sensitivity-adjusting

reading operation are converted into digital signals via an amplifier 116 and an A/D converter 117. The digital signal is supplied to a data comparator 124 of the controller 120 as lightness data corresponding to

5   the bright/dark pattern of the subject image. The lightness data are expressed by, e.g., 256 gray levels. The image data corresponding to each reading operation are converted into a lightness data value in the range of 0 to 255 and stored in the data comparator 124. A

10   specific example is shown in FIGS. 30A to 30E. FIGS. 30A to 30E show lightness data which are obtained when reading operation has been executed a predetermined number of times, and in which the image reading sensitivity increases with an increase in the number of

15   times reading operation is executed. For example, FIGS. 30A to 30E show how lightness data change in the columns when reading operation has been executed 16 times (FIG. 30A), 32 times (FIG. 30B), 64 times (FIG. 30C), 96 times (FIG. 30D) and 128 times (FIG. 30E).

20   The lightness data obtained when the reading operation has been executed 16 times and 32 times are data wherein the image reading sensitivity is low. Since the sensitivity is thus insufficient, there are columns in which the data value is "0" (lower limit). On the

25   other hand, the lightness data obtained when the reading operation has been executed 96 times and 128 times are data wherein the image reading sensitivity is

high. Since the sensitivity is too high, there are columns in which the data value is "255" (upper limit).

In S73 (the step of extracting a maximum value and a minimum value in each reading operation) of FIG. 28, a maximum value and a minimum value are extracted from the lightness data supplied to the data comparator 124. The extracted maximum and minimum values are output to the adder 125. In other words, the lightness data value indicating a maximum value (i.e., the gray level of the brightest pixel) and the lightness data value indicating a minimum value (i.e., the gray level of the darkest pixel) are extracted each time reading operation is executed.

Next, in S74 (the step of calculating a dynamic range in each reading operation) of FIG. 28, the adder 125 calculates the difference between the maximum and minimum values of lightness data in each reading operation as a dynamic range. The result of this calculation is stored in the RAM 130 through the use of the data selector 126. This dynamic range calculation step is executed each time reading operation is performed.

In S75 (the step of extracting a reading operation that exhibits a maximum dynamic range) of FIG. 28, the data selector 126 reads out dynamic ranges of reading operations from the RAM 130, and the readout dynamic ranges are supplied to the data comparator 124. On the

basis of the dynamic range changing tendency (FIG. 31)
relative to the number of times of a reading operation
is executed, a maximum value DLmax of the dynamic range
is determined in relation to the number of times a

5   reading operation is executed, and the number RCa of
times corresponding to the determined maximum value is
extracted.   In the example shown in FIGS. 30A to 30E,
the lightness data obtained in the 16th and 32nd
reading operations have a minimum value saturated at

10   the lower limit (=0), and the lightness data obtained
in the 96th and 128th reading operations has a maximum
value saturated at the upper limit (=255).   In
contrast, the lightness data obtained in the 64th
reading operation does not have a value that is

15   saturated at the upper or lower limit.   As a result,
the dynamic range of the lightness data obtained in the
64th reading operation is greater than the dynamic
ranges of the other lightness data.   Hence, the maximum
value is DLmax, and the number RCa of the reading

20   operation corresponding to that maximum value is 64.

     Next, S76 (the step of referring to and extracting
a sensitivity) of FIG. 28 is executed on the basis of
the extracted number RCa.   In the step, the image
reading sensitivity (i.e., the charge accumulating

25   period) corresponding to the number RCa of the reading
operation is extracted by referring to the table stored
in the RAM 130, i.e., the table of [the number of times

of reading operation] vs [image reading sensitivity
correspondence table].

In S77 (the step of setting the extracted
sensitivity) of FIG. 28, the main controller 123 causes
the data controller 122 to rewrite the data in the
sensitivity setting register 127, so that the image
reading sensitivity of the sensitivity setting register
127 is set at the extracted image reading sensitivity.
This brings an end to the optimal image reading
sensitivity setting based on the sensitivity-adjusting
reading operation.

According to the sensitivity setting method of the
sixth embodiment, one or more specific rows (specific
row section) of the photosensor array are selected, and
the sensitivity-adjusting reading operation (which
repeatedly reads a subject image at predetermined
intervals) is executed in the selected specific row
section after resetting operation. Hence, the subject
image can be read, with the image reading sensitivity
(charge accumulating period) being varied stepwise. In
comparison with the case where resetting operation is
repeated executed for each of the rows of the
photosensor array, as in the first to fifth
embodiments, the time needed for the sensitivity-
adjusting reading operation can be as short as
possible.

In the first to fifth embodiments, the

sensitivity-adjusting reading operation is executed for
the entire light-receiving area or a selected light-
receiving area of the photosensor array, and an optimal
image reading sensitivity is extracted on the basis of

5   the read image data corresponding to one frame. Unlike
these embodiments, the sixth embodiment uses image data
corresponding to one or several specific rows (specific
row section). In comparison with the foregoing
embodiments, the amount of data used for the extraction

10   of an optimal image reading sensitivity can be
significantly reduced, resulting in a remarkable
decrease in the processing load. In addition, the time
needed for the setting of an optimal image reading
sensitivity can be significantly shortened.

15   Furthermore, the sensitivity-adjusting reading
operation is limited to the specific row section.
Unlike the first to fifth embodiments, wherein the
sensitivity-adjusting reading operation is executed for
the entire light-receiving area of the photosensor

20   array or a selected portion thereof, the sixth
embodiment has significantly lowered the probability of
inclusion of an abnormal pixel (a missing point or a
twinkling point), which may be caused by a foreign
substance adhering to a target area, a defective

25   element of a photosensor, or the like. Hence, there is
a significantly lowered probability that an
inappropriate image reading sensitivity will be set due

to the existence of such an abnormal pixel.
Accordingly, a malfunction is prevented in fingerprint
recognition processing.

In the sixth embodiment, specific row section is a
central row (n/2-th row) and several rows located in
the vicinity thereof in a matrix of n rows × m columns
(n = 256, m = 196). Needless to say, the present
invention is not limited to this. The specific row
section may be selected from any area as long as that
area shows a clear brightness pattern (contrast) of a
subject image. For example, the specific row section
may be those located near the central row, or may be
selected from another area.

<Seventh Embodiment>

The seventh embodiment of a photosensor system
drive control method according to the present invention
will be described with reference to the accompanying
drawings.

In the sixth embodiment described above, the
sensitivity-adjusting reading operation is executed for
one or several specific rows (specific row section).
This significantly reduces the probability that an
abnormal pixel exits in the target specific row section
in comparison with the case where the entire light-
receiving area of a photosensor array or a selected
area thereof is subjected to the reading operation.
However, the probability that an abnormal pixel exists

in the specific row section is in no way "zero."

Like the sixth embodiment, the seventh embodiment
is intended to reliably prevent the adverse effects an
abnormal pixel may have when the sensitivity-adjusting

5   reading operation is performed for the specific row
section.   The controller applied to the seventh
embodiment is similar in structure to the controller
120 employed in the first, second and sixth embodiments
and is represented by the structural blocks shown in

10   FIG. 2.

FIG. 32 is a flowchart illustrating how the
controller 120 controls the operation of the
photosensor system in the seventh embodiment of the
present invention.   In the flowchart, the operations

15   executed up to the optimal image reading sensitivity
setting are illustrated.   FIG. 33 shows a specific row
section of the photosensor array for which the
sensitivity-adjusting reading operation is performed
according to the seventh embodiment, the specific row

20   section being illustrated as Rp in relation to a
subject image.   In the description below, reference
will be made to the structure of the photosensor system
shown in FIGS. 1 and 2, if required.   Similar or
corresponding structural elements will be denoted by

25   the same reference numerals as used in the description
of the sixth embodiment, and a simplified description
will be given of such structural elements.

The sensitivity-adjusting reading operation applied to the sensitivity adjusting method of the seventh embodiment is executed for a specific row Rp of a photosensor array 100 in which photosensors are arranged in units of a matrix pattern of 256 rows × 196 columns, as shown in FIG. 33. In the description below, it is assumed that an abnormal pixel IL3 exits at the position of row Rp and column Lq, and that the value of the lightness data at that position is "0", due to a foreign substance adhering to the sensing surface of the photosensor array, a defective element of the photosensor, or the like.

Step S81 (sensitivity-adjusting reading operation) of FIG. 32 is executed in a similar manner to that of S71 of the sixth embodiment. That is, the photosensors corresponding to the specific row Rp of the photosensor array 100 shown in FIG. 33 are controlled in such a manner that the charge accumulating period (i.e., the image reading sensitivity) varies stepwise at predetermined intervals. The sensitivity-adjusting reading operation is performed for a subject image at a plurality of image reading sensitivities, which correspond to the number of times reading operation has been executed. These operations are executed prior to the normal reading of the subject image.

Step S82 (image data conversion step) of FIG. 32, is executed in a similar manner to that of S72 of the

sixth embodiment. The image data read by the
sensitivity-adjusting reading operation are converted
into lightness data. The lightness data are supplied
to the controller 120 and stored in the RAM 130. A
5   specific example is shown in FIGS. 34A to 34E. Like
FIGS. 30A to 30E, FIGS. 34A to 34E show how lightness
data change in the columns when reading operation has
been executed 16 times (FIG. 34A), 32 times (FIG. 34B),
64 times (FIG. 34C), 96 times (FIG. 34D) and 128 times
10   (FIG. 34E). The lightness data obtained when the
reading operation has been executed 16 times and 32
times are data wherein the image reading sensitivity is
low. Since the sensitivity is thus insufficient, there
are columns in which the data value is "0" (lower
15   limit). On the other hand, the lightness data obtained
when the reading operation has been executed 96 times
and 128 times are data wherein the image reading
sensitivity is high. Since the sensitivity is too
high, there are columns in which the data value is
20   "255" (upper limit).

Next, step S83 (the step of extracting and
comparing the same-column data from the data of each
reading operation) shown in FIG. 32 is executed. In
this step, the data selector 126 extracts lightness
25   data of the same column from the lightness data stored
in the RAM 130 and corresponding to each reading
operation. The extracted lightness data are supplied

to the data comparator 124 so as to compare the
lightness data of the same column.

Then, step S84 (the step of determining a
variation in the same-column data) shown in FIG. 32 is
executed. This step is for determining whether there
is a column in which the lightness data remain the same
after each reading operation.

If there is a column in which the lightness data
do not changed, the pixels corresponding to this column
are regarded as abnormal ones, and the specific row
section for which the sensitivity-adjusting reading
operation is performed is determined as containing an
abnormal pixel.

If there is not a column in which the lightness
data remain the same, the specific row section for
which the sensitivity-adjusting reading operation is
performed is determined as not containing an abnormal
pixel.

A result of this determination is supplied from
the data comparator 124 to the main controller 123. In
the example shown in FIG. 37, the abnormal pixel IL3 is
present, and the lightness data corresponding to column
number Lq are "0" irrespective of the number of times
reading operation is executed. In other words, there
is a column in which the lightness data remain the same
after each reading operation, and row Rq is determined
to contain an abnormal pixel.

A description will be given of a specific method for checking the presence/absence of an abnormal pixel by detecting whether or not there is a column in which the lightness data do not changed before and after each reading operation. For example, the sensitivity-adjusting reading operation may be controlled as follows: Flags are set for the respective columns on the basis of the lightness data on the columns obtained by the first-time reading operation. The light data obtained by subsequent reading operations are compared with the lightness data obtained by the first-time reading operation. This comparison is executed for each of the columns. If the lightness data on a column differ from the original lightness data, the flag corresponding to that column is reset. As long as a pixel is normal, the lightness data on the pixel vary in accordance with a change in the image reading sensitivity. Hence, the flag of the pixel is reset. On the other hand, if the pixel is abnormal, the lightness data on the column containing the abnormal pixel do not vary even when the image reading sensitivity changes. The value of the lightness data is an upper-limit value, a lower-limit value or a constant in between, for example. Hence, the flag continues to be in the set state. As can be seen from this, an abnormal pixel present in a specific row section for which the sensitivity-adjusting reading

operation is to be executed can be detected by monitoring the states of the flags.

If step S84 (the step of determining a variation in the same-column data) determines that an abnormal pixel exists, step S85 (the step of changing the row section for which the sensitivity-adjusting reading operation) shown in FIG. 32 is executed. In this step, the main controller 123 causes the device controller 121 to change the specific row section for which the sensitivity-adjusting reading operation is to be executed. Thereafter, the operations starting from S81 (sensitivity-adjusting reading operation) are executed again. It is only required that the specific row section for which the sensitivity-adjusting reading operation is newly executed be a another specific row section other than the specific row section where the abnormal pixel IL3 is detected. For example, the another specific row section may be the one that is adjacent to row Rp in the upper or lower area, or may be the one that is away from that specific row section by a predetermined number of rows. The processing in steps S81-S84 is repeatedly executed until the specific row section for which the sensitivity-adjusting reading operation is to be executed is determined as not containing an abnormal pixel.

If step S84 (the step of determining a variation in the same-column data) determines that an abnormal

pixel does not exist in the specific row section for which the sensitivity-adjusting reading operation is to be executed, step S86 (the step of extracting a maximum value and a minimum value in each reading operation) shown in FIG. 32 is executed. In this step, maximum and minimum values are extracted from the lightness data obtained in each reading operation and supplied to the data comparator 124, and output to the adder 125, as in step S73 of the sixth embodiment.

Subsequently, step S87 (the step of calculating a dynamic range in each reading operation), step S88 (the step of extracting a reading operation that exhibits a maximum dynamic range), step S89 (the step of referring to and extracting a sensitivity) and step S90 (the step of setting the extracted sensitivity) shown in FIG. 32, are sequentially executed. These steps are similar to steps S74 to S77 of the sixth embodiment described above. That is, the dynamic range of the lightness data obtained in each reading operation is calculated by the adder, and then the data comparator 124 checks the dynamic range changing tendency (FIG. 31) relative to the number of times a reading operation is executed, and detects the reading operation in which the dynamic range is maximal. The image reading sensitivity (the charge accumulating period) corresponding to this reading operation is set in the sensitivity setting register 127, thereby bringing an end to the optimal

image reading sensitivity setting based on the sensitivity-adjusting reading operation.

In the sensitivity setting method of the seventh embodiment, if an abnormal pixel, which is due to a foreign substance adhering to the sensing surface of the photosensor array, any defective element of the photosensor, or the like, is present in the specific row section for which the sensitivity-adjusting reading operation is to be executed, such an abnormal pixel can be easily detected. Based on this detection, the sensitivity-adjusting reading operation is executed for another specific row section where no abnormal pixel exists. In this manner, lightness data corresponding to a specific row section containing no abnormal pixel is acquired as lightness data for sensitivity adjustment. Even if the specific row section originally selected for the sensitivity-adjusting reading operation contains an abnormal pixel, the adverse effects arising from such an abnormal pixel can be obviated.

In addition, an optimal image reading sensitivity is unconditionally determined on the basis of the dynamic range of light data acquired by the sensitivity-adjusting reading operation. Therefore, even when the sensitivity-adjusting reading operation is to be executed for a specific row section different from the originally selected specific row section, the

image reading sensitivity is kept optimal. Normal
reading operation for a subject image can be executed
in a reliable manner irrespective of the ambient
conditions, such as the illuminated state of the

5   environment. Accordingly, a malfunction is prevented
in fingerprint recognition processing or the like.

In the sixth and seventh embodiments described
above, the specific row section for which the
sensitivity-adjusting reading operation is to be

10   executed is predetermined, for example, in the center
of the photosensor. The present invention is not
limited to this. That is, the specific row section
need not be designated beforehand. For example, the
entire area of a subject image or a predetermined area

15   thereof may be read at an arbitrary image reading
sensitivity. In this case, a specific row section most
suitable for image reading is extracted, and one or
several rows of the specific row section may be
determined on the basis of the extracted data.An image

20   reading sensitivity (charge accumulating period)
setting method applicable to the sensitivity-adjusting
reading operation in the above-described embodiments
will be described with reference to the several views
of the accompanying drawing. In the description below,

25   reference will be made to the structure of the
photosensor system shown in FIGS. 1 and 2 and the
structure of the photosensor system shown in FIGS. 39A

and 40, if required.

FIGS. 35A to 35J are timing charts showing the first embodiment of the image reading sensitivity (charge accumulating period) setting method, which is applicable to the sensitivity-adjusting reading operation of the first to fifth embodiments.

According to the image reading sensitivity setting method of this embodiment, as shown in FIGS. 35A to 35D, reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn are simultaneously applied to respective top gate lines 101 connected to the top gate terminals TG of double-gate photosensors 10 in the row direction, thereby simultaneously starting a reset period T_{reset}, and initializing the double-gate photosensors 10 of respective rows.

The reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn simultaneously fall to end the reset period T_{reset}. Then, charge accumulating periods T_1, T_2, $\cdots$, T_{n-1}, T_n of the double-gate photosensors 10 on all the rows simultaneously start, and charges (holes) are generated and accumulated in the channel regions in accordance with light quantities entering the double-gate photosensors 10 of respective rows from their top gate terminal (21) side.

As shown in FIGS. 35E to 35I, a pre-charge pulse ϕpg and readout pulses $\phi B1$, $\phi B2$, $\cdots$, ϕBn corresponding to the bottom gate line 102 are applied

to change stepwise the charge accumulating periods T_1, T_2, $\cdots$, T_{n-1}, T_n set for respective rows by a predetermined delay time T_{delay} for respective rows. In this case, the delay time T_{delay} is equal to or longer than the total time of the reset period T_{reset}, pre-charge time T_{prch}, and readout time T_{read}.

As shown in FIG. 35J, therefore, drain voltages VD1, VD2, ..., VDm varying in correspondence to the charge accumulated in the charge accumulating periods T1, T2, ..., Tn, which are between the end of the reset period T_{reset} and the start of the readout time T_{read} (i.e., the application of the readout pulses ϕB1, ϕB2, $\cdots$, ϕBn), are sequentially read out.

Hence, image data read at reading sensitivities different for respective rows constituting a subject image can be attained by one reading operation of the subject image in sensitivity-adjusting reading operation performed prior to sensitivity setting processing as described in the above embodiments.

FIGS. 36A to 36J are timing charts showing the second embodiment of the image reading sensitivity (charge accumulating period) setting method, which is applicable to the sensitivity-adjusting reading operation of the first to fifth embodiments.

According to the image reading sensitivity setting method of this embodiment, as shown in FIGS. 36A to 36D, the reset pulses ϕT1, ϕT2, $\cdots$, ϕTn are

sequentially applied to the respective top gate lines 101 connected to the top gate terminals TG of the double-gate photosensors 10 in the row direction at a time interval of a predetermined delay time T_{delay}, thereby starting the reset period T_{reset}, and initializing the double-gate photosensors 10 of respective rows.

The reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn fall to end the reset period T_{reset}. Then, charge accumulating periods TA_1, TA_2, $\cdots$, TA_{n-1}, TA_n sequentially start, and charges (holes) are generated and accumulated in the channel regions in accordance with light quantities entering the double-gate photosensors 10 of respective rows from their top gate terminal (21) side.

As shown in FIGS. 36E to 36I, the pre-charge pulse ϕpg and readout pulses ϕBn, $\phi Bn-1$, $\cdots$, $\phi B2$, $\phi B1$ corresponding to the bottom gate line 102 are applied to change stepwise the charge accumulating periods TA_1, TA_2, $\cdots$, TA_{n-1}, TA_n set for respective rows by the predetermined delay time T_{delay} for respective rows after the final reset pulse ϕTn falls. In this case, the delay time T_{delay} is equal to or longer than the total time of the reset period T_{reset}, pre-charge time T_{prch}, and readout time T_{read}.

As shown in FIG. 36J, therefore, drain voltages VD1, VD2, ..., VDm varying in correspondence to the charge accumulated in the charge accumulating periods

TAn, $TAn-1$, ..., $TA1$, which are between the end of the reset period T_{reset} and the start of the readout time T_{read} (i.e., the application of the readout pulses ϕBn, $\phi Bn-1$, ..., $\phi B1$), are sequentially read out.

By this sensitivity-adjusting reading operation, the charge accumulating periods TA_1, TA_2, ..., TA_{n-1}, TA_n set for respective rows increase at a time interval twice the predetermined delay time T_{delay}, and thus image data read at reading sensitivities set at a sensitivity adjustment width of several rows or more can be obtained by reading operation of one frame.

FIGS. 37A to 37L are timing charts illustrating an embodiment of the sensitivity-adjusting reading operation, which is applicable to the sensitivity-adjusting reading operation of the sixth and seventh embodiments. In the description below, it is assumed that the one specific row section for which the sensitivity-adjusting reading operation is to be executed is a row located in the center.

As shown in FIGS. 37A to 37E, the image reading sensitivity setting method of the embodiment initializes only the double-gate photosensors of a central row (n/2n-th row), i.e., a specific row, of the photosensor array shown in FIG. 40. More specifically, waves $\phi T1$ to $\phi Tn/2-1$ and $\phi Tn/2+1$ to ϕTn applied to the first to (n/2-1)-th rows and (n/2+1)-th to n-th rows, which are among the top gate lines 101 connected

to the top gate terminals TG of the double-gate

photosensors 10 in the row direction, are set at a low

level, and a single reset pulse $\phi Tn/2$ is applied only

to the n/2-th row. In this manner, the reset period

5　　T_{reset} is started, and only the double-gate

photosensors 10 of the (n/2)-th row are initialized.

Then, the reset pulse $\phi Tn/2$ falls and the reset

period T_{reset} ends. Thereafter, the charge

accumulating period starts, and charges (holes) are

10　　generated and accumulated in the channel regions in

accordance with the amount of light entering the

double-gate photosensors 10 of the n/2-th row from

their top gate terminal (21) side.

Subsequently, as shown in FIGS. 37F to 37K,

15　　precharge signal ϕpg and readout pulse $\phi Bn/2$, which is

predetermined for the bottom gate lines 102 of the n/2-

th row, are alternately applied at predetermined

intervals Tint a number of times (x times, x: an

integer larger than 1). Waves $\phi B1$ to $\phi Bn/2-1$ and

20　　$\phi Bn/2+1$ to ϕBn applied to the bottom gate lines 102 of

the first to (n/2-1)-th rows and (n/2+1)-th to n-th

rows are set at a low level.

As shown in FIG. 37L, therefore, drain voltages

VD1, VD2, …, VDm varying in correspondence to the

25　　charge accumulated in the charge accumulating periods

TB1, TB2, …, TBx, which are between the end of the

reset period T_{reset} and the start of the readout time

T_{read} (i.e., the application of the readout pulses $\phi Bn/2$), are sequentially read out.

By this sensitivity-adjusting reading operation, the charge accumulating period of a specific row section increases stepwise at predetermined time intervals T_{int}. Hence, image data is read from a subject image, with the image corresponding to the specific row section being read at a plurality of different image reading sensitivities.

In the sensitivity-adjusting reading operation described above, the photosensors corresponding to one of the specific row section are reset at a time, and reading operation is repeatedly executed with respect to them. In this connection, it should be noted that the amount of charge accumulated in each photosensor may be varied by the readout operation. To solve this problem, the charge accumulating period of each reading operation may be corrected in accordance with an actual charge accumulating period on the basis of the correspondence between the number of times reading operation is performed and the amount of charge accumulated.

As described above, according to the sensitivity setting methods of the above embodiments, sensitivity-adjusting reading operation is executed with respect to a subject image while simultaneously changing the image reading sensitivity stepwise. On the basis of the

distribution of the dynamic ranges of the lightness

data obtained at each image reading sensitivity or the

linearly differentiated values of the dynamic ranges, .

an image reading sensitivity which ensures an optimal

5   image reading state is determined easily. This image

reading sensitivity (charge accumulating period) can be

used as an optimal sensitivity, so that the sensitivity

setting is easy. Moreover, since the sensitivity

setting processing can be executed using an actual

10   subject, it is not necessary to use a standard sample

or the like. Even when the lightness of the subject

image varies in response to changes in the environment

light, an optimal image reading sensitivity can be set

in accordance with the changes in the environmental

15   light. This has eliminated the need to employ a

circuit specially designed for sensing the

environmental light. Further, even if the photosensors

vary in characteristics, the image data obtained from

these photosensors is used for determining an optimal

20   sensitivity. Hence, the adverse effects arising from

the characteristic variations can be remarkably

suppressed.

According to the sensitivity setting method of the

fifth embodiment, abnormal values, which deviate from

25   the main change trend of lightness data, are removed

from the lightness data, and a row or rows that are in

an optimal image reading state are selected in a simple

manner on the basis of the abnormal value-free

lightness data. The image reading sensitivity (charge

accumulating period) set for that specific row section

can be used as an optimal sensitivity. According to

5   the sensitivity setting method of the sixth and seventh

embodiments, only a specific row section of the

photosensor array is used in the sensitivity-adjusting

reading operation. Alternatively, the presence of an

abnormal pixel is determined, and a specific row

10   section that does not contain an abnormal pixel is used

for the sensitivity-adjusting reading operation.

Therefore, the image reading sensitivity can be set at

an optimal value without being adversely affected by an

abnormal pixel, which is due to a foreign substance

15   adhering to the sensing surface of the photosensor

array, a defect of the photosensor element, or the

like.

In each of the embodiments described above, the

sensitivity-adjusting reading operation is executed

20   prior to the normal reading operation. The present

invention is not limited to this. For example, the

sensitivity-adjusting reading operation may be executed

in the standby state, i.e., the state where the

photosensor system is operating but a subject has not

25   yet been placed.

In addition, the sensitivity-adjusting reading

operation was described as being performed whenever the

normal reading operation is executed for a subject image. The present invention is not limited to this. For example, the sensitivity-adjusting reading operation may be performed only when there is a change in the use environment, or when a predetermined length of time has elapsed.

The image reading sensitivity (charge accumulating period) setting method applied to sensitivity setting processing according to the present invention is not limited to the above embodiments. As far as image data of a subject image can be obtained at different reading sensitivities, e.g., a series of processes described in the prior art: reset operation → charge accumulating operation → pre-charge operation → readout operation can be repeated a plurality of number of times at different reading sensitivities, thereby obtaining image data at different reading sensitivities. Alternatively, any other methods may also be employed.

A description will now be given of the effective voltages of signals which are applied to the top and bottom gate terminals TG and BG in the sensitivity-adjusting reading operation and the image reading operation when the photosensor array of the present invention is made of a double-gate photosensor 10, and of a method for controlling the effective voltage to be an optimal value.

As is apparent from FIGS. 35A to 35H, 36A to 36H,

37A to 37J and 41A to 41C, the top gate terminal TG receives a high-level signal voltage Vtgh as a reset pulse only for a very short time (T_{reset}), and a low-level signal voltage Vtgl for the remaining relatively

5   long period in sensitivity-adjusting reading operation and image reading operation. In the sensitivity-adjusting reading and image reading periods, the effective voltage applied to the top gate terminal TG greatly shifts to the low-level side. Since an optimal

10   charge accumulating period set for image reading operation is changed and set in accordance with the ambient illuminance or the like if necessary, the effective voltage applied to the top gate terminal TG inevitably varies.

15   In the sensitivity-adjusting reading operation and the image reading operation, the bottom gate terminal BG receives a high-level signal voltage Vbgh only for a very short time (T_{read}), and a low-level signal voltage Vbgl for the remaining relatively long period. In the

20   sensitivity-adjusting reading and image reading periods, the effective voltage applied to the bottom gate terminal BG also greatly shifts to the low-level side. Since an optimal charge accumulating period set for image reading operation is changed and set in

25   accordance with the ambient illuminance or the like if necessary, the effective voltage applied to the bottom gate terminal BG inevitably varies.

If such a voltage shifted to a voltage of
a specific polarity is kept applied to the gate
electrode, the gate electrode traps holes to degrade
the element characteristics of the double-gate

5   photosensor and change the sensitivity characteristics.

To prevent this, an effective voltage adjusting
period for correcting effective voltages applied to
the top and bottom gate terminals TG and BG is set
after the sensitivity-adjusting reading and image

10   reading periods. During the effective voltage
adjusting period, predetermined correction signals are
applied. One of them is for setting an effective
voltage applied to the top gate terminal TG to an
optimal value Vte of the effective voltage of the top

15   gate electrode set in accordance with the sensitivity
characteristics of the double-gate photosensor.
Another correction signal is for setting an effective
voltage applied to the bottom gate terminal BG to an
optimal value Vbe of the effective voltage of the

20   bottom gate electrode. This can suppress changes in
sensitivity characteristics caused by degradation in
the element characteristics of the photosensor, and can
improve the reliability of the photosensor system.

In a photosensor system drive control method

25   according to the present invention, the sensitivity-
adjusting reading operation of each embodiment can be
performed immediately before the image reading.

operation, and the effective voltage adjusting period
can be set after the image reading period. Operations
of this case will be described with reference to the
Figures.

5   FIGS. 38A to 38H are timing charts showing an
embodiment wherein the effective voltage adjusting
period is set after the sensitivity-adjusting reading
and image reading periods.

As the drive control method during the
10   sensitivity-adjusting reading period, the drive control
method in FIGS. 36A to 36H described above is applied.
The same reference numerals denote the same parts, and
a description thereof will be omitted. The reset
pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn are pulse signals whose high
15   and low levels are signal voltages Vtgh and Vtgl,
respectively. The readout pulses $\phi B1$, $\phi B2$, $\cdots$, ϕBn
are pulse signals whose high and low levels are signal
voltages Vbgh and Vbgl, respectively. As the drive
control method during the sensitivity-adjusting reading
20   period, the operation shown in FIGS. 35A to 35H or the
operation shown in FIGS. 37A to 37J may be applied.
Needless to say, the present invention is not limited
to these methods.

The drive control method during the image reading
25   period is based on the conventional photosensor system
drive control method shown in FIGS. 41A to 41D.
To shorten the operation time, photosensors are driven

by overlapping the charge accumulating periods of respective rows at timings so as not to overlap reset, pre-charge, and readout pulses. That is, as shown in FIGS. 38A to 38C, the reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn are sequentially applied to the respective top gate lines 101 connected to the top gate terminals TG of the double-gate photosensors 10 in the row direction, thereby starting the reset period T_{reset}, and initializing the double-gate photosensors 10 of respective rows. Similar to the above-described sensitivity-adjusting reading operation, the reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn are pulse signals whose high and low levels are the signal voltages Vtgh and Vtgl, respectively. Except for timings at which the reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn of high-level Vtgh are applied, the low-level signal voltage Vtgl is applied.

The reset pulses $\phi T1$, $\phi T2$, $\cdots$, ϕTn fall to end the reset period T_{reset}. Then, optimal light accumulating periods Ta obtained by each embodiment for respective rows based on sensitivity-adjusting reading operation sequentially start, and charges (holes) are generated and accumulated in the channel regions in accordance with light quantities entering the double-gate photosensors 10 from their top gate electrode side. As shown in FIG. 38G, pre-charge operation of applying the pre-charge signal ϕpg to start the pre-charge period T_{prch}, and applying the

pre-charge voltage V_{prch} to the data line 103 to cause the drain electrode of the double-gate photosensor 10 to hold a predetermined voltage is performed during the light accumulating period Ta. As shown in FIGS. 38D to 38F, the readout pulses $\phi B1$, $\phi B2$, $\cdots$, ϕBn are sequentially applied in units of rows to the bottom gate lines 102 of double-gate photosensors 10 in which the optimal light accumulating period Ta and pre-charge period T_{prch} end. Then, the readout period T_{read} starts, and voltage changes VD corresponding to charges accumulated in the double-gate photosensors 10 are read out from the output circuit section 113 via the data lines 103, as shown in FIG. 38H. Similar to the sensitivity-adjusting reading operation described above, the readout pulses $\phi B1$, $\phi B2$, $\cdots$, ϕBn are pulse signals whose high and low levels are at the signal voltages Vbgh and Vbgl, respectively. Till timings at which the readout pulses $\phi B1$, $\phi B2$, $\cdots$, ϕBn of high-level Vbgh are applied, the low-level signal voltage Vbgl has been applied.

After image reading operation is completed for all the rows, effective voltage adjustment operation of adjusting the shifts of the effective voltages of signals applied to each gate electrode in the sensitivity-adjusting reading and image reading periods and optimizing the effective voltages is executed in the effective voltage adjusting period. More

specifically, as shown in FIGS. 38A to 38C, the top

gate line 101 of each row receives a correction signal

having a high-level period (Ttph) and low-level period

(Ttpl) so as to attain a predetermined effective

5   voltage capable of adjusting the effective voltage of a

signal voltage applied to the top gate line 101, i.e.,

top gate terminal TG of the double-gate photosensor 10

in response to a reset pulse in the sensitivity-

adjusting reading and image reading periods to an

10   optimal value Vte set in advance in accordance with the

sensitivity characteristics of the double-gate

photosensor 10.

Similarly, the bottom gate line 102 of each row

receives a correction signal having a high-level period

15   (Tbph) and low-level periods (Tbpla and Tbplb) so as to

attain a predetermined effective voltage capable of

adjusting the effective voltage of a signal voltage

applied to the bottom gate line 102, i.e., bottom gate

terminal BG of the double-gate photosensor 10 in

20   response to a readout pulse to an optimal value Vbe

set in advance in accordance with the sensitivity

characteristics of the double-gate photosensor 10.

As a result, the effective values of voltages

applied to the top and bottom gate terminals TG and BG

25   of the photosensor element can be set to optimal values

to suppress changes in sensitivity characteristics

caused by degradation in the element characteristics of

the photosensor, and to improve the reliability of the
photosensor system.